



Rating plug, 1250A, IZMX40

Part no. +IZMX-RP40-1250  
Article no. 126416

## Delivery program

Product range			Accessories
Accessories			Options / accessories trip blocks
Accessories			Rating Plug (rate current module)
			The rated current can be reduced by changing the rating plug, for example, in order to adapt to changed conditions in the application. The rating plug's nominal value must be less than or equal to the basic device's rated current. The rating plug can be replaced on site without replacing the transformer. 200 A, 250 A and 300 A rating plugs cannot be combined with P-trip units.
Rated current	$I_n$	A	1250
Suitable for circuit-breaker $I_u$ =			$1600 \text{ A} \leq I_u \leq 4000 \text{ A}$
For use with			IZMX40

## Design verification as per IEC/EN 61439

Technical data for design verification			
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70

## Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Current transformer (EC002048)			
Electric engineering, automation, process control engineering / Signal processing / Transformer / Current transformer (ecl@ss8.1-27-21-09-02 [AAB626011])			
Model			Through-feed current converter
Primary rated current		A	1250
Secondary rated current		A	0
Secondary rated apparent power		VA	0
Accuracy class			1
Over voltage limiting factor			-
Calibrated			No
With shock protection			Yes
Opening height		mm	0
Opening width		mm	0
Opening diameter		mm	0
Snap mounting			No
With copper rail			No
Secondary connection			-
Number of primary inputs			1