



**Shunt release (for power circuit breaker);48VDC**

**Part no.  
Article no.**

**+IZMX-ST48DC  
123616**

## Delivery program

Product range			Accessories
Accessories			Remote switching
Accessories			Shunt release (for power circuit breaker)
			Can be combined with an undervoltage release or a second shunt release.
Maximum operating frequency	Actuations/ minute		3
			Limited to 3/min due to the high pick-up current for 35 ms. Please note - the circuit-breaker's switching frequency = 60/h
Rated control voltage	$U_s$	V	48 V DC
Operating range	$x U_s$	Factor	0,7 - 1,1
max. holding current	$I_n$	A	0.089
max. pick-up current (35ms)	$I_n$	A	10
max. continuous power	AC/DC	VA/W	5
max. pull-in power (35ms)	AC/DC	VA/W	530
Circuit-breaker total switching time	@ $U_s=100\%$	ms	22
For use with			IZMX16..., IZMX40... INX16..., INX40...
<b>Notes</b>			
Suitable for continuous commands (100% DF)			

## Design verification as per IEC/EN 61439

Technical data for design verification			
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70

## Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Shunt release (for power circuit breaker) (EC001023)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Full load current trip (ecl@ss8.1-27-37-04-18 [AKF016010])			
Rated control supply voltage $U_s$ at AC 50HZ	V		0 - 0
Rated control supply voltage $U_s$ at AC 60HZ	V		0 - 0
Rated control supply voltage $U_s$ at DC	V		48 - 48
Voltage type for actuating			DC
Initial value of the undelayed short-circuit release - setting range	A		0
End value adjustment range undelayed short-circuit release	A		0
Type of electric connection			Flat plug-in connection
Number of contacts as normally open contact			0
Number of contacts as normally closed contact			0
Number of contacts as change-over contact			0
Suitable for power circuit breaker			Yes
Suitable for off-load switch			Yes
Suitable for motor safety switch			No
Suitable for overload relay			No