

RCD/MCB combination switch, 16A, 100mA, miniature circuit-br. type B trip characteristic, 3p, residual current circuit-br. trip characteristic: A



Part no. Article no. Catalog No.

FRBMM-B16/3/01-A 170782 FRBMM-B16/3/01-A

Similar to illustration

Delivery program

Basic function			Combined RCD/MCB devices
Number of poles			3 pole
Tripping characteristic			В
Application			Switchgear for industrial and advanced commercial applications
Rated current	I _n	А	16
Rated switching capacity according to IEC/EN 61009		kA	10
Rated fault current	$I_{\Delta N}$	А	0.1
Tripping		А	non-delayed
Product range			FRBmM
Sensitivity			Pulse-current sensitive
Impulse withstand current			Partly surge-proof 250 A
Contact sequence			

Technical data

Electrical			
Sensitivity			Pulse-current sensitive
Rated current	I _n	А	16
Tripping characteristic			В

Design verification as per IEC/EN 61439

In	А	16
P _{vid}	W	0
P _{vid}	W	8.3
P _{vs}	W	0
P _{diss}	W	0
	°C	-25
	°C	40
		0
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Does not apply, since the entire switchgear needs to be evaluated.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Meets the product standard's requirements.
	P _{vid} P _{vid} P _{vs}	P _{vid} W P _{vid} W P _{vs} W P _{diss} W °C

10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 6.0

Circuit breakers and fuses (EG000020) / Earth leakage circuit breaker (EC000905)

Electric engineering, automation, process control engineering / Electrical installation, device / Residual current protection system / MCB/RCCB combination (ecl@ss8.1-27-14-22-07 [AFZ810012])

Number of poles (total)		3
Number of protected poles		3
Nominal rated voltage	V	415
Nominal rated current	А	16
Rated fault current	А	0.1
Leakage current type		А
Current limiting class		3
Rated short-circuit breaking capacity EN 60898	kA	10
Rated short-circuit breaking capacity IEC 60947-2	kA	0
Frequency		50 Hz
Release characteristic		В
Concurrently switching N-neutral		No
Over voltage category		3
Pollution degree		2
Width in number of modular spacings		4
Built-in depth	mm	75.5
Suitable for flush-mounted installation		No
Degree of protection (IP)		IP20
Surge current capacity	kA	0.25
Voltage type		AC
Antinuisance tripping version		No



