



Connections, front, 3200A, IZMX40, 3 p, withdrawable

Part no. IZMX-TF403-3200W-1
Article no. 184179
Catalog No. 67C2975H03

Delivery program

Product range			Accessories
Accessories			Main terminal kits
Accessories			Front connections
			This connection kit comes with front terminals for connection to the cassette. The circuit-breaker can be connected directly with CU bars on the rear flanged connection. If necessary, the optional front terminals can be installed before the circuit-breaker is installed in the enclosure. This way, the final connection to the circuit-breaker can be made from the front.
Rated current	I_n	A	3200
Pole			3
For use with			IZMX40...3...32W INX40...3...32W
Information about equipment supplied			Each set includes the connections for top and bottom. 3-pole for 6 connections, 4-pole for 8 connections Screws, washers, and supports are included as standard.
Installation type			Withdrawable

Design verification as per IEC/EN 61439

Technical data for design verification			
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70

Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Connection vane/phase spreader (EC002019)	
Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Connection vane/phase spreader (ecl@ss8.1-27-37-13-05 [ACN990009])	
Suitable for number of poles	3

Dimensions

The drawing shows a front view of the connection kit on the left and a detailed view of the terminal arrangement on the right. The detailed view shows three poles with a 4-pole label. Dimensions include 115mm between poles, 106mm total height, 264.5mm total width, and 12.5mm terminal height. Terminal widths are 50mm, 80mm, and 11mm. A hole diameter of $\varnothing 11$ is indicated.

Current range	Cu amount	X
800A, 1000A, 1250A, 1600A	1x10	10
2000A, 2500A	2x10	20
3200A	3x10	30

