

Circuit-breaker, 3p, 1000 A, fixed

Powering Business Worldwide*

Part no. IZMX40B3-A10F
Article no. 149422
Catalog No. RES6103B22-NMNN2MN1X

Delivery program

zomor, program			
Product range			Air circuit-breakers/switch-disconnectors
Product range			Open circuit-breakers
Current Range			Up to 4000 A
Protective function			System protection
Installation type			Fixed
Construction size			IZMX40
Release system			Electronic release
Standard/Approval			IEC
Number of poles			3 pole
Degree of Protection			IP20, IP55 with protective cover, IP41 door sealing frame
			optionally fittable by user with comprehensive accessories
Rated current = rated uninterrupted current	$\boldsymbol{I}_n = \boldsymbol{I}_u$	Α	1000
Bemessungsgrenzkurzschlussausschaltvermögen bis 440V/690V 42/42	I _{cu}	kA	66
Bemessungsbetriebskurzschlussausschaltvermögen bis 440V/690V 42/42	I _{cs}	kA	66
Overload release, min.	I _r	Α	500
Overload release, max.	I _r	Α	1000
Non-delayed	$I_i = I_n \times \dots$		2 - 12
<u>I</u> >			
Notes			
Main terminals must be separately ordered.			

Technical data

General

General			
Standards			IEC/EN 60947
Ambient temperature			
Storage	θ	°C	-40 - +70
Operating (open)		°C	-25 - +70
Mounting position			30° 30°
			30° 30°
Utilization category			В
Degree of Protection			IP20, IP55 with protective cover, IP41 door sealing frame
Direction of incoming supply			as required
Main conducting paths			
Rated current = rated uninterrupted current	$I_n = I_u$	Α	1000
Rated uninterrupted current at 50 °C	I _u	Α	1000
Rated uninterrupted current at 60 °C	I _u	Α	1000
Rated uninterrupted current at 70 °C	I _u	Α	1000
Rated impulse withstand voltage	U _{imp}	V AC	12000
Rated operational voltage	U _e	V AC	690

Use in IT electrical power networks up to U = 440 V	I _{IT}	kA	36
Overvoltage category/pollution degree			III/3
Rated insulation voltage	Ui	V	1000
Switching capacity			
Rated short-circuit making capacity	I _{cm}		
up to 440 V 50/60 Hz	I _{cm}	kA	145
up to 690 V 50/60 Hz	I _{cm}	kA	145
Rated short-time withstand current 50/60 Hz			
t=1s	I _{cw}	kA	66
t = 3 s	I _{cw}	kA	53
Rated short-circuit breaking capacity I _{cn}	I _{cn}		
IEC/EN 60947 operating sequence I _{cu} 0-t-C0			
up to 240 V 50/60 Hz	I _{cu}	kA	66
up to 440 V 50/60 Hz	I _{cu}	kA	66
up to 690 V 50/60 Hz	I _{cu}	kA	66
IEC/EN 60947 operating sequence I _{cs} 0-t-CO-t-CO	·cu		
		LΛ	CC CC
up to 240 V 50/60 Hz	I _{cs}	kA	66
up to 440 V 50/60 Hz	I _{cs}	kA	66
up to 690 V 50/60 Hz	I _{cs}	kA	66
Operating times			
Closing delay via spring release		ms	35
Total opening delay via shunt release		ms	22
Total opening delay via undervoltage release		ms	37
Total opening delay on non-delayed short-circuit release (up to complete arc quenching)		ms	45
Maximum operating frequency	Operations/h		60
Heat dissipation at rated current I_n			
Fixed mounting		W	55
Weight			
Fixed mounting			
3-pole		kg	43
4-pole		kg	56
Terminal capacities			
Copper bar			
Fixed mounting		mm	1 v 60 v 10
Black		mm	1 x 60 x 10 These are values used in separate switchgear. The actual values will depend on the temperature around the circuit-breaker, which is influenced by the ambient temperature, the degree of protection (IP), the mounting height, the partitions, and any external ventilation. Depending on the specific switchgear design, this may result in derating, which can then be compensated for by increasing the cross-sectional area. Temperature rise tests in the specific switchgear can provide specific and detailed information.
			Permissible continuous current for circuit-breakers operating in switchboards at various internal ambient temperatures. The switchboard's internal ambient temperature should be estimated using the calculation methods of IEC regulation.

Design verification as per IEC/EN 61439

•			
Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	1000
Equipment heat dissipation, current-dependent	P_{vid}	W	55
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.

10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation prot. (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss8.1-27-37-04-09 [AJZ716010])

Rated permanent current lu Rated voltage V 690 - 690 Rated short-circuit breaking capacity lcu at 400 V, 50 Hz Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release AD 0 - 12000 Adjustment range undelayed short-circuit release AD 0 - 12000 Adjustment range undelayed short-circuit release AD 0 - 12000 Alperated earth fault protection No Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Switched-off indicator available With under voltage release With under voltage release Number of poles			
Rated short-circuit breaking capacity Icu at 400 V, 50 Hz Overload release current setting A 500 - 1000 Adjustment range short-term delayed short-circuit release A 0 - 12000 Adjustment range undelayed short-circuit release A 2000 - 12000 Integrated earth fault protection Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release KA 66 500 - 1000 No Rail connection No Rail connection Built-in device fixed built-in technique No O O Ves No No No No No No No No No N	Rated permanent current lu	Α	1000
Overload release current setting Adjustment range short-term delayed short-circuit release A 0 - 12000 Adjustment range undelayed short-circuit release A 2000 - 12000 Integrated earth fault protection Integrated earth fault protection No Type of electrical connection of main circuit Device construction Built-in device fixed built-in technique Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release No	Rated voltage	V	690 - 690
Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release A 2000 - 12000 Integrated earth fault protection No Type of electrical connection of main circuit Device construction Built-in device fixed built-in technique Suitable for DIN rail (top hat rail) mounting No DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release No	Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	kA	66
Adjustment range undelayed short-circuit release Integrated earth fault protection No Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting No DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release A 2000 - 12000 No Rail connection Built-in device fixed built-in technique No DIN rail (top hat rail) mounting No O O Ves No	Overload release current setting	Α	500 - 1000
Integrated earth fault protection Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release No Rail connection Built-in device fixed built-in technique No No O O O O O O Number of auxiliary contacts as normally closed contact O Number of auxiliary contacts as normally open contact Ves With under voltage release	Adjustment range short-term delayed short-circuit release	Α	0 - 12000
Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release Rail connection Built-in device fixed built-in technique No No No No No No No No No N	Adjustment range undelayed short-circuit release	Α	2000 - 12000
Device construction Built-in device fixed built-in technique Suitable for DIN rail (top hat rail) mounting No DIN rail (top hat rail) mounting optional No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact 2 Switched-off indicator available With under voltage release No	Integrated earth fault protection		No
Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact 0 Number of auxiliary contacts as normally open contact 0 Number of auxiliary contacts as change-over contact 2 Switched-off indicator available With under voltage release No	Type of electrical connection of main circuit		Rail connection
DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact 2 Switched-off indicator available With under voltage release No	Device construction		Built-in device fixed built-in technique
Number of auxiliary contacts as normally closed contact 0 Number of auxiliary contacts as normally open contact 0 Number of auxiliary contacts as change-over contact 2 Switched-off indicator available With under voltage release No	Suitable for DIN rail (top hat rail) mounting		No
Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release No	DIN rail (top hat rail) mounting optional		No
Number of auxiliary contacts as change-over contact 2 Switched-off indicator available With under voltage release No	Number of auxiliary contacts as normally closed contact		0
Switched-off indicator available Yes With under voltage release No	Number of auxiliary contacts as normally open contact		0
With under voltage release No	Number of auxiliary contacts as change-over contact		2
	Switched-off indicator available		Yes
Number of poles 3	With under voltage release		No
	Number of poles		3
Position of connection for main current circuit Back side	Position of connection for main current circuit		Back side
Type of control element Push button	Type of control element		Push button
Complete device with protection unit Yes	Complete device with protection unit		Yes
Motor drive integrated No	Motor drive integrated		No
Motor drive optional Yes	Motor drive optional		Yes
Degree of protection (IP)	Degree of protection (IP)		IP20