

Circuit-breaker, 4p, 3200 A, fixed

Powering Business Worldwide*

Part no. IZMX40H4-V32F
Article no. 149931
Catalog No. RESC324B52QNMNN2MN1X

Delivery program

Delivery brodiam			
Product range			Air circuit-breakers/switch-disconnectors
Product range			Open circuit-breakers
Current Range			Up to 4000 A
Protective function			Selective operation
Installation type			Fixed
			Main terminals must be separately ordered.
Construction size			IZMX40
Release system			Electronic release
Standard/Approval			IEC
Number of poles			4 pole
Degree of Protection			IP20, IP55 with protective cover, IP41 door sealing frame
			suitable for zone selectivity optionally fittable by user with comprehensive accessories
Rated current = rated uninterrupted current	$I_n=I_u$	Α	3200
up to 440 V 50/60 Hz	I _{cu}	kA	105
up to 440 V 50/60 Hz	I _{cs}	kA	105
Overload release, min.	I _r	Α	1600
Overload release, max.	I _r	Α	3200
Non-delayed	$I_i = I_n x \dots$		2 - 12, OFF
Delayed X >	$I_{sd} = I_r x \dots$		2 - 10

Technical data

i Commodi data			
General			
Standards			IEC/EN 60947
Ambient temperature			
Storage	8	°C	-40 - +70
Ambient temperature		°C	-25 - +70
Mounting position			30° 30°
			30° 30°
Utilization category			В
Degree of Protection			IP20, IP55 with protective cover, IP41 door sealing frame
Direction of incoming supply			as required
Main conducting paths			
Rated current = rated uninterrupted current	$I_n = I_u$	Α	3200
Rated uninterrupted current at 50 °C	l _u	Α	3200
Rated uninterrupted current at 60 °C	Iu	Α	3200
Rated uninterrupted current at 70 °C	I _u	Α	3200

Rated impulse withstand voltage	U_{imp}	V AC	12000
Rated operational voltage	U _e	V AC	690
Use in IT electrical power networks up to U = 440 V	I _{IT}	kA	57.6
Overvoltage category/pollution degree			III/3
Rated insulation voltage	U_{i}	V	1000
Switching capacity			
Rated short-circuit making capacity	I _{cm}		
up to 440 V 50/60 Hz	I _{cm}	kA	231
up to 690 V 50/60 Hz	I _{cm}	kA	166
Rated short-time withstand current 50/60 Hz			
t = 1 s	I _{cw}	kA	85
t = 3 s	I _{cw}	kA	66
Rated short-circuit breaking capacity I _{cn}	I _{cn}		
IEC/EN 60947 operating sequence I _{cu} O-t-CO			
up to 240 V 50/60 Hz	I _{cu}	kA	105
up to 440 V 50/60 Hz	I _{cu}	kA	105
up to 690 V 50/60 Hz	I _{cu}	kA	75
IEC/EN 60947 operating sequence I _{cs} 0-t-C0-t-C0	cu		
up to 240 V 50/60 Hz	I _{cs}	kA	105
up to 440 V 50/60 Hz		kA	105
	I _{CS}		
up to 690 V 50/60 Hz	I _{cs}	kA	75
Operating times			-
Closing delay via spring release		ms	35
Total opening delay via shunt release		ms	22
Total opening delay via undervoltage release		ms	37
Total opening delay on non-delayed short-circuit release (up to complete arc		ms	45
quenching)		1113	10
Maximum operating frequency	Operations/h		60
Heat dissipation at rated current I _n			
Fixed mounting		W	385
Weight			
Fixed mounting			
3-pole		kg	43
4-pole		kg	56
Terminal capacities Copper bar			
Fixed mounting			
Fixed mounting Black		mm	3 x 80 x 10
DIGCE		mm	These are values used in separate switchgear. The actual values will depend on
			the temperature around the circuit-breaker, which is influenced by the ambient temperature, the degree of protection (IP), the mounting height, the partitions, and any external ventilation. Depending on the specific switchgear design, this may result in derating, which can then be compensated for by increasing the cross-sectional area. Temperature rise tests in the specific switchgear can provide specific and detailed information.
			Permissible continuous current for circuit-breakers operating in switchboards at various internal ambient temperatures. The switchboard's internal ambient temperature should be estimated using the calculation methods of IEC regulation.

Design verification as per IEC/EN 61439

Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	3200
Equipment heat dissipation, current-dependent	P _{vid}	W	385
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70
IEC/EN 61439 design verification			

10.2 Strength of materials and parts	
10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eator provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation prot. (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss8.1-27-37-04-09 [AJZ716010])

Rated voltage Rated short-circuit breaking capacity Icu at 400 V, 50 Hz Overload release current setting Al 1600 - 3200 Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Al 6400 - 32000 Adjustment range undelayed short-circuit release Al 6400 - 38400 Integrated earth fault protection Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Switched-off indicator available With under voltage release Number of poles Number of noinection for main current circuit Device control element Very of control element Complete device with protection unit Motor drive integrated Motor drive optional Motor drive optional			
Rated short-circuit breaking capacity lou at 400 V, 50 Hz KA 105 Overload release current setting A 1600 - 3200 Adjustment range short-term delayed short-circuit release A 6400 - 32000 Adjustment range undelayed short-circuit release A 6400 - 38400 Integrated earth fault protection No Rail connection Type of electrical connection of main circuit Built-in device fixed built-in technique Suitable for DIN rail (top hat rail) mounting Built-in device fixed built-in technique Number of auxiliary contacts as normally closed contact No Number of auxiliary contacts as normally open contact 2 Switched-off indicator available Yes With under voltage release No Number of poles 4 Position of connection for main current circuit Back side Type of control element Push button Complete device with protection unit Yes Motor drive integrated No Motor drive optional Yes	Rated permanent current lu	Α	3200
Overload release current setting A 1600 - 3200 Adjustment range short-term delayed short-circuit release A 6400 - 32000 Adjustment range undelayed short-circuit release A 6400 - 38400 Integrated earth fault protection No Rail connection Type of electrical connection of main circuit Built-in device fixed built-in technique Device construction Built-in device fixed built-in technique Suitable for DIN rail (top hat rail) mounting No Number of auxiliary contacts as normally closed contact No Number of auxiliary contacts as normally open contact 2 Switched-off indicator available Yes With under voltage release No Number of poles 4 Position of connection for main current circuit Back side Type of control element Push button Complete device with protection unit Yes Motor drive integrated No Motor drive optional Yes	Rated voltage	V	690 - 690
Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release Integrated earth fault protection Type of electrical connection of main circuit Device construction Built-in device fixed built-in technique Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Switched-off indicator available With under voltage release Number of poles Number of poles Number of poles Number of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional	Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	kA	105
Adjustment range undelayed short-circuit release Integrated earth fault protection Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally pen contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release Number of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive integrated Motor drive optional	Overload release current setting	Α	1600 - 3200
Integrated earth fault protection Type of electrical connection of main circuit Device construction Built-in device fixed built-in technique Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as normally open contact Vitual of indicator available Ves With under voltage release With under voltage release Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Wood office of the control of	Adjustment range short-term delayed short-circuit release	Α	6400 - 32000
Type of electrical connection of main circuit Device construction Device construction Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional	Adjustment range undelayed short-circuit release	Α	6400 - 38400
Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available Viru under voltage release Number of poles Position of connection for main current circuit Appendic of control element Complete device with protection unit Motor drive integrated Motor drive optional Built-in device fixed built-in technique No No No A A A A A A A A A A A A A	Integrated earth fault protection		No
Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of pindicator available No No No No Number of poles No No No No No No Nord of connection for main current circuit Notor drive integrated No	Type of electrical connection of main circuit		Rail connection
DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of indicator available With under voltage release With under voltage release No No Number of poles Act side Type of control element Complete device with protection unit Motor drive integrated Motor drive optional No No No No No No No No No N	Device construction		Built-in device fixed built-in technique
Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Switched-off indicator available Yes With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional O O O O O O O O O O O O O	Suitable for DIN rail (top hat rail) mounting		No
Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional O O O O O O O O O O O O O	DIN rail (top hat rail) mounting optional		No
Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional 2 Sack side Push button Yes No No Yes	Number of auxiliary contacts as normally closed contact		0
Switched-off indicator available With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional Yes Yes Yes Yes No Yes Yes Yes Yes Yes Yes	Number of auxiliary contacts as normally open contact		0
With under voltage release No Number of poles 4 Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional No	Number of auxiliary contacts as change-over contact		2
Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional A 4 Back side Push button Yes No No Yes	Switched-off indicator available		Yes
Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional Back side Push button Yes No Yes	With under voltage release		No
Type of control element Complete device with protection unit Motor drive optional Push button Yes No Yes	Number of poles		4
Complete device with protection unit Yes Motor drive integrated No Motor drive optional Yes	Position of connection for main current circuit		Back side
Motor drive integrated No Motor drive optional Yes	Type of control element		Push button
Motor drive optional Yes	Complete device with protection unit		Yes
	Motor drive integrated		No
Degree of protection (IP)	Motor drive optional		Yes
	Degree of protection (IP)		IP20