

### Circuit-breaker, 4p, 2500 A, fixed

Powering Business Worldwide\*

Part no. IZMX40N4-P25F Article no. 149914

Catalog No. RES8254B12NNMNN2MN1X

## **Delivery program**

| benvery program                             |                        |    |  |
|---|------------------------|----|--|
| Product range                               |                        |    | Air circuit-breakers/switch-disconnectors  |
| Product range                               |                        |    | Open circuit-breakers  |
| Current Range                               |                        |    | Up to 4000 A   |
| Protective function                         |                        |    | Professional protection  |
| Installation type                           |                        |    | Fixed  |
| Construction size                           |                        |    | IZMX40   |
| Release system                              |                        |    | Electronic release   |
| Standard/Approval                           |                        |    | IEC  |
| Number of poles                             |                        |    | 4 pole   |
| Degree of Protection                        |                        |    | IP20, IP55 with protective cover, IP41 door sealing frame  |
|   |                        |    | suitable for zone selectivity suitable for communication with integrated system monitor with integrated test possibility with graphic LCD color display optionally fittable by user with comprehensive accessories |
| Rated current = rated uninterrupted current | $I_n = I_u$            | Α  | 2500   |
| up to 440 V 50/60 Hz                        | I <sub>cu</sub>        | kA | 85   |
| up to 440 V 50/60 Hz                        | I <sub>cs</sub>        | kA | 85   |
| Overload release, min.                      | I <sub>r</sub>         | Α  | 1250   |
| Overload release, max.                      | I <sub>r</sub>         | Α  | 2500   |
| Non-delayed                                 | $I_i = I_n x \dots$    |    | 2 - 12, OFF  |
| Delayed                                     | $I_{sd} = I_r x \dots$ |    | 2 - 10   |

## **Technical data**

| General                                     |                |    |   |
|---|----------------|----|---|
| Standards                                   |                |    | IEC/EN 60947  |
| Ambient temperature                         |                |    |   |
| Storage                                     | θ              | °C | -25 - +70 (device with LCD-display -20 - +70)             |
| Operating (open)                            |                | °C | -25 - +70 (device with LCD-display -20 - +70)             |
| Mounting position                           |                |    | 30° 30°   |
|   |                |    | 30° 30°   |
| Utilization category                        |                |    | В   |
| Degree of Protection                        |                |    | IP20, IP55 with protective cover, IP41 door sealing frame |
| Direction of incoming supply                |                |    | as required   |
| Main conducting paths                       |                |    |   |
| Rated current = rated uninterrupted current | $I_n = I_u$    | Α  | 2500  |
| Rated uninterrupted current at 50 °C        | l <sub>u</sub> | Α  | 2500  |
| Rated uninterrupted current at 60 °C        | I <sub>u</sub> | Α  | 2500  |

| Dated uninterwented assurant at 70 °C   |                  | ۸    | 2500  |
|---|------------------|------|---|
| Rated uninterrupted current at 70 °C  | l <sub>u</sub>   | A    | 2500  |
| Rated impulse withstand voltage   | U <sub>imp</sub> | V AC | 12000   |
| Rated operational voltage   | U <sub>e</sub>   | V AC | 690   |
| Use in IT electrical power networks up to $U = 440 \text{ V}$                           | I <sub>IT</sub>  | kA   | 57.6  |
| Overvoltage category/pollution degree   |                  |      | III/3   |
| Rated insulation voltage  | Ui               | ٧    | 1000  |
| Switching capacity  |                  |      |   |
| Rated short-circuit making capacity   | I <sub>cm</sub>  |      |   |
| up to 440 V 50/60 Hz  | I <sub>cm</sub>  | kA   | 187   |
| up to 690 V 50/60 Hz  | I <sub>cm</sub>  | kA   | 166   |
| Rated short-time withstand current 50/60 Hz   |                  |      |   |
| t = 1 s   | I <sub>cw</sub>  | kA   | 85  |
| t=3s  | I <sub>cw</sub>  | kA   | 66  |
| Rated short-circuit breaking capacity I <sub>cn</sub>                                   | I <sub>cn</sub>  |      |   |
| IEC/EN 60947 operating sequence I <sub>cu</sub> 0-t-C0                                  |                  |      |   |
| up to 240 V 50/60 Hz  | I <sub>cu</sub>  | kA   | 85  |
|   |                  |      |   |
| up to 440 V 50/60 Hz  | I <sub>cu</sub>  | kA   | 85  |
| up to 690 V 50/60 Hz  | I <sub>cu</sub>  | kA   | 75  |
| IEC/EN 60947 operating sequence I <sub>cs</sub> 0-t-C0-t-C0                             |                  |      |   |
| up to 240 V 50/60 Hz  | I <sub>cs</sub>  | kA   | 85  |
| up to 440 V 50/60 Hz  | I <sub>cs</sub>  | kA   | 85  |
| up to 690 V 50/60 Hz  | I <sub>cs</sub>  | kA   | 75  |
| Operating times   |                  |      |   |
| Closing delay via spring release  |                  | ms   | 35  |
| Total opening delay via shunt release   |                  | ms   | 22  |
| Total opening delay via undervoltage release  |                  | ms   | 37  |
|   |                  |      |   |
| Total opening delay on non-delayed short-circuit release (up to complete arc quenching) |                  | ms   | 45  |
| Maximum operating frequency   | Operations/h     |      | 60  |
| Heat dissipation at rated current I <sub>n</sub>  |                  |      |   |
| Fixed mounting  |                  | W    | 235   |
| Weight  |                  |      |   |
| Fixed mounting  |                  |      |   |
| 3-pole  |                  | kg   | 43  |
| 4-pole  |                  | kg   | 56  |
| Terminal capacities   |                  |      |   |
| Copper bar  |                  |      |   |
| Fixed mounting  |                  |      |   |
| Black   |                  | mm   | 2 x 80 x 10   |
|   |                  |      | These are values used in separate switchgear. The actual values will depend on the temperature around the circuit-breaker, which is influenced by the ambient temperature, the degree of protection (IP), the mounting height, the partitions, and any external ventilation. Depending on the specific switchgear design, this may result in derating, which can then be compensated for by increasing the cross-sectional area. Temperature rise tests in the specific switchgear can provide specific and detailed information. |
|   |                  |      | Permissible continuous current for circuit-breakers operating in switchboards at various internal ambient temperatures. The switchboard's internal ambient temperature should be estimated using the calculation methods of IEC regulation.   |
| Notes   |                  |      | IZMX-DTP-PTM external voltage measuring module required   |

# Design verification as per IEC/EN 61439

| Technical data for design verification                   |           |    |      |
|--|-----------|----|------|
| Rated operational current for specified heat dissipation | In        | Α  | 2500 |
| Equipment heat dissipation, current-dependent            | $P_{vid}$ | W  | 235  |
| Operating ambient temperature min.                       |           | °C | -25  |

| Operating ambient temperature max.   | °C | 70   |
|--|----|--|
| EC/EN 61439 design verification  |    |  |
| 10.2 Strength of materials and parts   |    |  |
| 10.2.2 Corrosion resistance  |    | Meets the product standard's requirements.   |
| 10.2.3.1 Verification of thermal stability of enclosures   |    | Meets the product standard's requirements.   |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat   |    | Meets the product standard's requirements.   |
| 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects |    | Meets the product standard's requirements.   |
| 10.2.4 Resistance to ultra-violet (UV) radiation   |    | Meets the product standard's requirements.   |
| 10.2.5 Lifting   |    | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.6 Mechanical impact   |    | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.7 Inscriptions  |    | Meets the product standard's requirements.   |
| 10.3 Degree of protection of ASSEMBLIES  |    | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.4 Clearances and creepage distances   |    | Meets the product standard's requirements.   |
| 10.5 Protection against electric shock   |    | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.6 Incorporation of switching devices and components   |    | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.7 Internal electrical circuits and connections  |    | Is the panel builder's responsibility.   |
| 10.8 Connections for external conductors   |    | Is the panel builder's responsibility.   |
| 10.9 Insulation properties   |    |  |
| 10.9.2 Power-frequency electric strength   |    | Is the panel builder's responsibility.   |
| 10.9.3 Impulse withstand voltage   |    | Is the panel builder's responsibility.   |
| 10.9.4 Testing of enclosures made of insulating material   |    | Is the panel builder's responsibility.   |
| 10.10 Temperature rise   |    | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating   |    | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| 10.12 Electromagnetic compatibility  |    | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| 10.13 Mechanical function  |    | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.                         |
|  |    |  |

### **Technical data ETIM 6.0**

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation prot. (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss8.1-27-37-04-09 [AJZ716010])

| Rated permanent current lu Rated voltage Rated short-circuit breaking capacity lcu at 400 V, 50 Hz Rated short-circuit breaking capacity lcu at 400 V, 50 Hz A Rotel short-circuit breaking capacity lcu at 400 V, 50 Hz A Rotel short-circuit release current setting A Rotel politic range short-term delayed short-circuit release A Rotel politic range undelayed short-circuit  | protection (ecl@ss8.1-27-37-04-09 [AJZ716010])            |    |  |
|--|---|----|--|
| Rated short-circuit breaking capacity Icu at 400 V, 50 Hz  Overload release current setting  Aligustment range short-term delayed short-circuit release  Aligustment range undelayed short-circuit release  Aligus | Rated permanent current lu                                | Α  | 2500                                     |
| Overload release current setting       A       1250 - 2500         Adjustment range short-term delayed short-circuit release       A       5000 - 25000         Adjustment range undelayed short-circuit release       A       5000 - 30000         Integrated earth fault protection       No       Rail connection         Type of electrical connection of main circuit       Built-in device fixed built-in technique         Suitable for DIN rail (top hat rail) mounting       No         DIN rail (top hat rail) mounting optional       No         Number of auxiliary contacts as normally closed contact       0         Number of auxiliary contacts as normally open contact       0         Number of auxiliary contacts as change-over contact       2         Switched-off indicator available       Yes         With under voltage release       No         Number of poles       4         Position of connection for main current circuit       Back side   | Rated voltage   | V  | 690 - 690                                |
| Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release A 5000 - 20000  No  Type of electrical connection of main circuit  Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact  Switched-off indicator available With under voltage release Number of poles Position of connection for main current circuit  A 5000 - 25000  No  No  Rail connection  No  No  O  O  O  O  O  O  O  O  O  O  O  O  O   | Rated short-circuit breaking capacity Icu at 400 V, 50 Hz | kA | 85                                       |
| Adjustment range undelayed short-circuit release Integrated earth fault protection Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release Number of poles Number of connection for main current circuit A Source A So | Overload release current setting                          | Α  | 1250 - 2500                              |
| Integrated earth fault protection Type of electrical connection of main circuit  Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release Number of poles Number of connection for main current circuit No  | Adjustment range short-term delayed short-circuit release | Α  | 5000 - 25000                             |
| Type of electrical connection of main circuit  Device construction  Suitable for DIN rail (top hat rail) mounting  DIN rail (top hat rail) mounting optional  No  No  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Switched-off indicator available  With under voltage release  Number of poles  No  No  Rail connection  Built-in device fixed built-in technique  No  No  No  No  Vol  Position of connection for main current circuit  Rail connection  Built-in device fixed built-in technique  No  No  No  No  Switched-off individent available  Yes  No  Back side  | Adjustment range undelayed short-circuit release          | Α  | 5000 - 30000                             |
| Device construction  Built-in device fixed built-in technique  Suitable for DIN rail (top hat rail) mounting  DIN rail (top hat rail) mounting optional  No  No  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Switched-off indicator available  Ves  With under voltage release  No  Number of poles  Position of connection for main current circuit  Built-in device fixed built-in technique  No  No  No  Built-in device fixed built-in technique  No  No  No  Built-in device fixed built-in technique  | Integrated earth fault protection                         |    | No                                       |
| Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No Number of auxiliary contacts as normally closed contact 0 Number of auxiliary contacts as normally open contact 0 Number of auxiliary contacts as change-over contact 2 Switched-off indicator available Ves With under voltage release No Number of poles Position of connection for main current circuit No Na  | Type of electrical connection of main circuit             |    | Rail connection                          |
| DIN rail (top hat rail) mounting optional  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  2  Switched-off indicator available  With under voltage release  No  Number of poles  Position of connection for main current circuit  No  No  Back side   | Device construction                                       |    | Built-in device fixed built-in technique |
| Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Switched-off indicator available  Yes  With under voltage release  No  Number of poles  Position of connection for main current circuit  O  Number of auxiliary contacts as normally open contact  2  Switched-off indicator available  Yes  No  Back side  | Suitable for DIN rail (top hat rail) mounting             |    | No                                       |
| Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Switched-off indicator available  With under voltage release  No  Number of poles  Position of connection for main current circuit  O  Ves  No  Back side  | DIN rail (top hat rail) mounting optional                 |    | No                                       |
| Number of auxiliary contacts as change-over contact  Switched-off indicator available  Yes  With under voltage release  No  Number of poles  Position of connection for main current circuit  Back side  | Number of auxiliary contacts as normally closed contact   |    | 0  |
| Switched-off indicator available  With under voltage release  With under voltage release  No  Number of poles  Position of connection for main current circuit  Back side  | Number of auxiliary contacts as normally open contact     |    | 0  |
| With under voltage release No Number of poles 4 Position of connection for main current circuit Back side  | Number of auxiliary contacts as change-over contact       |    | 2  |
| Number of poles 4 Position of connection for main current circuit Back side  | Switched-off indicator available                          |    | Yes                                      |
| Position of connection for main current circuit  Back side   | With under voltage release                                |    | No                                       |
|  | Number of poles   |    | 4  |
| T ( )  | Position of connection for main current circuit           |    | Back side                                |
| Type or control element Push button  | Type of control element                                   |    | Push button                              |
| Complete device with protection unit  Yes  | Complete device with protection unit                      |    | Yes                                      |
| Motor drive integrated No  | Motor drive integrated                                    |    | No                                       |
| Motor drive optional Yes   | Motor drive optional                                      |    | Yes                                      |
| Degree of protection (IP)  | Degree of protection (IP)                                 |    | IP20                                     |