

Circuit-breaker, 4p, 2500 A, withdrawable

Powering Business Worldwide*

Part no. IZMX40N4-V25W Article no. 149994

Catalog No. RES8254W52NNMNN2MNDX

Delivery program

Product range			Air circuit-breakers/switch-disconnectors
Product range			Open circuit-breakers
Current Range			Up to 4000 A
Protective function			Selective operation
Installation type			Withdrawable
			Cassette must be separately ordered.
			Main terminals must be separately ordered.
Construction size			IZMX40
Release system			Electronic release
Standard/Approval			IEC
Number of poles			4 pole
Degree of Protection			IP20, IP55 with protective cover, IP41 door sealing frame
			suitable for zone selectivity optionally fittable by user with comprehensive accessories
Rated current = rated uninterrupted current	$\boldsymbol{I}_n = \boldsymbol{I}_u$	Α	2500
up to 440 V 50/60 Hz	I _{cu}	kA	85
up to 440 V 50/60 Hz	I _{cs}	kA	85
Overload release, min.	I _r	Α	1250
Overload release, max.	I _r	Α	2500
Non-delayed I	$I_i = I_n x \dots$		2 - 12, OFF
Delayed >	$I_{sd} = I_r x \dots$		2 - 10

Technical data

Toommour data			
General			
Standards			IEC/EN 60947
Ambient temperature			
Storage	θ	°C	-40 - +70
Ambient temperature		°C	-25 - +70
Mounting position			30° 30°
			30° 30°
Utilization category			В
Degree of Protection			IP20, IP55 with protective cover, IP41 door sealing frame
Direction of incoming supply			as required
Main conducting paths			
Rated current = rated uninterrupted current	$I_n = I_u$	Α	2500
Rated uninterrupted current at 50 °C	Iu	Α	2500

Rated uninterrupted current at 60 °C

Α

2500

Rated uninterrupted current at 70 °C	l _u	Α	2500
Rated impulse withstand voltage	U _{imp}	V AC	12000
Rated operational voltage	U _e	V AC	690
Use in IT electrical power networks up to U = 440 V	I _{IT}	kA	57.6
Overvoltage category/pollution degree			III/3
Rated insulation voltage	Ui	V	1000
Switching capacity			
Rated short-circuit making capacity	I _{cm}		
up to 440 V 50/60 Hz	I _{cm}	kA	187
up to 690 V 50/60 Hz	I _{cm}	kA	166
Rated short-time withstand current 50/60 Hz			
t = 1 s	I _{cw}	kA	85
t = 3 s	I _{cw}	kA	66
Rated short-circuit breaking capacity I _{cn}	I _{cn}		
IEC/EN 60947 operating sequence I _{cu} 0-t-C0			
up to 240 V 50/60 Hz	I _{cu}	kA	85
up to 440 V 50/60 Hz	I _{cu}	kA	85
up to 690 V 50/60 Hz		kA	75
IEC/EN 60947 operating sequence I _{cs} O-t-CO-t-CO	I _{cu}	N/A	
up to 240 V 50/60 Hz		kΛ	85
	I _{cs}	kA	
up to 440 V 50/60 Hz	I _{cs}	kA	85
up to 690 V 50/60 Hz	I _{cs}	kA	75
Operating times			
Closing delay via spring release		ms	35
Total opening delay via shunt release		ms	22
Total opening delay via undervoltage release		ms	37
The large is a delication of the desired delication in the large for the second state of			as .
Total opening delay on non-delayed short-circuit release (up to complete arc quenching)		ms	45
Maximum operating frequency	Operations/h		60
Heat dissipation at rated current I _n			
Withdrawable units (switch with cassette)		W	350
Weight Withdrawable			
		ka	70
3-pole 4-pole		kg kg	86
Cassette		ĸy	00
3 pole		kg	27
4 pole		kg	35
Terminal capacities		"9	
Copper bar			
Withdrawable units			
Black		mm	2 x 80 x 10
			These are values used in separate switchgear. The actual values will depend on the temperature around the circuit-breaker, which is influenced by the ambient temperature, the degree of protection (IP), the mounting height, the partitions, and any external ventilation. Depending on the specific switchgear design, this may result in derating, which can then be compensated for by increasing the cross-sectional area. Temperature rise tests in the specific switchgear can provide specific and detailed information.
			Permissible continuous current for circuit-breakers operating in switchboards at various internal ambient temperatures. The switchboard's internal ambient temperature should be estimated using the calculation methods of IEC regulation.
Decign verification of per IEC/EN 61/20			
Design verification as per IEC/EN 61439			

Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	2500

Equipment heat dissipation, current-dependent	P _{vid}	W	350
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70
EC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switch gear must be observed. $\label{eq:constraint}$
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switch gear must be observed. $\label{eq:constraint}$
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation prot. (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss8.1-27-37-04-09 [AJZ716010])

Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit 2 See See See See See See See See See Se	protection (eci@sss.1-27-37-04-09 [AJZ/10010])		
Rated short-circuit breaking capacity lou at 400 V, 50 Hz Overload release current setting Adjustment range short-term delayed short-circuit release Adjustment range short-term delayed short-circuit release Adjustment range undelayed	Rated permanent current lu	А	2500
Overload release current setting Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release Integrated earth fault protection Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (to	Rated voltage	V	690 - 690
Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release A 5000 - 30000 No Type of electrical connection of main circuit Agil connection Rail connection Built-in device slide-in technique (withdrawable) Built-in device slide-in technique (withdrawable) Built-in device slide-in technique (withdrawable) No DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release Number of poles Position of connection for main current circuit Back side Type of control element Complete device with protection unit A 5000 - 30000 No No Occupance Switched-off indicator available Ves Back side Push button Ves Complete device with protection unit	Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	kA	85
Adjustment range undelayed short-circuit release Integrated earth fault protection Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit	Overload release current setting	Α	1250 - 2500
Integrated earth fault protection Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No	Adjustment range short-term delayed short-circuit release	Α	5000 - 25000
Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of connection for main current circuit Type of control element Complete device with protection unit	Adjustment range undelayed short-circuit release	Α	5000 - 30000
Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available Vith under voltage release Vith under voltage release Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Built-in device slide-in technique (withdrawable) No O O O O O O O O O O O O O	Integrated earth fault protection		No
Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No No Number of connection for main current circuit Type of control element Complete device with protection unit No	Type of electrical connection of main circuit		Rail connection
DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit No No Auxiliary contacts as normally open contact Ves Sack side Yes Yes Yes	Device construction		Built-in device slide-in technique (withdrawable)
Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Number of auxiliary contacts as normally closed contact O Rumber of auxiliary contacts as normally open contact Ves Seach Seach Side Push button Yes	Suitable for DIN rail (top hat rail) mounting		No
Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit O O O O O O O O O O O O O	DIN rail (top hat rail) mounting optional		No
Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit 2 See See See See See See See See See Se	Number of auxiliary contacts as normally closed contact		0
Switched-off indicator available With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Yes Yes A Back side Push button Yes	Number of auxiliary contacts as normally open contact		0
With under voltage release No Number of poles 4 Position of connection for main current circuit Type of control element Complete device with protection unit No Number of poles 4 Back side Push button Yes	Number of auxiliary contacts as change-over contact		2
Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit A 4 Back side Push button Yes	Switched-off indicator available		Yes
Position of connection for main current circuit Type of control element Complete device with protection unit Complete Merchant State State Back side Push button Yes	With under voltage release		No
Type of control element Push button Complete device with protection unit Yes	Number of poles		4
Complete device with protection unit Yes	Position of connection for main current circuit		Back side
	Type of control element		Push button
Motor drive integrated No.	Complete device with protection unit		Yes
110	Motor drive integrated		No

Motor drive optional	Yes
Degree of protection (IP)	IP20