



Undervoltage release 60 VDC

Part no. **IZMX-UVR60DC**
Article no. **124099**

Delivery program

| | | | |
|--------------------------------------|-----------------------|--------|--|
| Product range | | | Accessories |
| Accessories | | | Remote switching |
| Accessories | | | Undervoltage release |
| | | | Cannot be combined with a second shunt release. |
| Maximum operating frequency | Actuations/ minute | | 3 |
| | | | Limited to 3/min due to the high pick-up current for 35 ms. Please note - the circuit-breaker's switching frequency = 60/h |
| Rated control voltage | U_s | V | 60 V DC |
| Operating range | $x U_s$ | Factor | 0,85 - 1,1 |
| max. holding current | I_n | A | 0.07 |
| max. pick-up current (35ms) | I_n | A | 12.5 |
| max. continuous power | AC/DC | VA/W | 5 |
| max. pull-in power (35ms) | AC/DC | VA/W | 890 |
| Circuit-breaker total switching time | @ $U_s=100\%$ | ms | 37 |
| For use with | | | IZMX16..., IZMX40... INX16..., INX40... |
| Instructions | | | An additional control circuit terminal block is required for retrofitting. For fixed mounting circuit-breakers → #156593 and withdrawable unit circuit-breakers → #156590 |
| Notes | | | |
| Can be continuously ON (100% DF) | | | |

Design verification as per IEC/EN 61439

| | | | |
|--|--|----|-----|
| Technical data for design verification | | | |
| Operating ambient temperature min. | | °C | -25 |
| Operating ambient temperature max. | | °C | 70 |

Technical data ETIM 6.0

| | | | |
|---|--|---|-------------------------|
| Low-voltage industrial components (EG000017) / Under voltage coil (EC001022) | | | |
| Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Undervoltage trip (ecl@ss8.1-27-37-04-17 [AKF015010]) | | | |
| Rated control supply voltage U_s at AC 50HZ | | V | 0 - 0 |
| Rated control supply voltage U_s at AC 60HZ | | V | 0 - 0 |
| Rated control supply voltage U_s at DC | | V | 60 - 60 |
| Voltage type for actuating | | | DC |
| Type of electric connection | | | Flat plug-in connection |
| Number of contacts as normally open contact | | | 0 |
| Number of contacts as normally closed contact | | | 0 |
| Number of contacts as change-over contact | | | 0 |
| Delayed | | | No |
| Suitable for power circuit breaker | | | Yes |
| Suitable for off-load switch | | | Yes |
| Suitable for motor safety switch | | | No |
| Suitable for overload relay | | | No |