

Circuit-breaker, 3p, 320A, withdrawable unit

Part no. NZMH3-A320-SVE Article no. 168913 Catalog No. NZMH3-A320-SVE



Similar to illustration

Design ver	ification as r	oer IEC/EN 61439

Design Verification as per IEC/EN 61439			
Technical data for design verification			
Equipment heat dissipation, current-dependent	P _{vid}	W	78.64
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects $$			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switch gear must observed. $\label{eq:specification}$
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switch gear must observed. $\label{eq:specification}$
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation prot. (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss8.1-27-37-04-09 [AJZ716010])

protection (ecl@ss8.1-27-37-04-09 [AJZ716010])		
Rated permanent current lu	А	320
Rated voltage	V	690 - 690
Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	kA	150
Overload release current setting	А	250 - 320
Adjustment range short-term delayed short-circuit release	Α	0 - 0
Adjustment range undelayed short-circuit release	А	1920 - 3200
Integrated earth fault protection		No
Type of electrical connection of main circuit		Screw connection
Device construction		Built-in device plug-in technique

DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of indicator available No No Number of poles No No Number of poles Switched-off indicator available No No Number of poles Rocker lever Complete device with protection unit No Motor drive integrated No		
Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No Switched-off indicator available No With under voltage release No Number of poles 3 Position of connection for main current circuit Front side Type of control element Complete device with protection unit Wotor drive integrated No Motor drive optional No Yes	Suitable for DIN rail (top hat rail) mounting	No
Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact No Switched-off indicator available With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional O O O O O O O O O O O O O	DIN rail (top hat rail) mounting optional	No
Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional O No No No No No Ves	Number of auxiliary contacts as normally closed contact	0
Switched-off indicator available With under voltage release No Number of poles Superition of connection for main current circuit Superition of control element Superition of control eleme	Number of auxiliary contacts as normally open contact	0
With under voltage release No Number of poles 3 Position of connection for main current circuit Front side Type of control element Complete device with protection unit Yes Motor drive optional No Motor drive optional	Number of auxiliary contacts as change-over contact	0
Number of poles 3 Position of connection for main current circuit Front side Rocker lever Complete device with protection unit Motor drive integrated Motor drive optional 3 Rocker lever No Yes	Switched-off indicator available	No
Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional Front side Rocker lever Yes Yes	With under voltage release	No
Type of control element Complete device with protection unit Motor drive optional Rocker lever Yes No Yes	Number of poles	3
Complete device with protection unit Yes Motor drive integrated No Motor drive optional Yes	Position of connection for main current circuit	Front side
Motor drive integrated No Motor drive optional Yes	Type of control element	Rocker lever
Motor drive optional Yes	Complete device with protection unit	Yes
	Motor drive integrated	No
Degree of protection (IP)	Motor drive optional	Yes
	Degree of protection (IP)	IP20