



## Circuit-breaker, 3p, 400A, plug-in module

Part no. **NZMN3-VE400-SVE**  
 Article no. **168481**  
 Catalog No. **NZMN3-VE400-SVE**

Similar to illustration

## Design verification as per IEC/EN 61439

| Technical data for design verification   |                  |   |  |
|--|------------------|---|--|
| Equipment heat dissipation, current-dependent  | P <sub>vid</sub> | W | 48   |
| IEC/EN 61439 design verification   |                  |   |  |
| 10.2 Strength of materials and parts   |                  |   |  |
| 10.2.2 Corrosion resistance  |                  |   | Meets the product standard's requirements.   |
| 10.2.3.1 Verification of thermal stability of enclosures   |                  |   | Meets the product standard's requirements.   |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat   |                  |   | Meets the product standard's requirements.   |
| 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects |                  |   | Meets the product standard's requirements.   |
| 10.2.4 Resistance to ultra-violet (UV) radiation   |                  |   | Meets the product standard's requirements.   |
| 10.2.5 Lifting   |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.6 Mechanical impact   |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.7 Inscriptions  |                  |   | Meets the product standard's requirements.   |
| 10.3 Degree of protection of ASSEMBLIES  |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.4 Clearances and creepage distances   |                  |   | Meets the product standard's requirements.   |
| 10.5 Protection against electric shock   |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.6 Incorporation of switching devices and components   |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.7 Internal electrical circuits and connections  |                  |   | Is the panel builder's responsibility.   |
| 10.8 Connections for external conductors   |                  |   | Is the panel builder's responsibility.   |
| 10.9 Insulation properties   |                  |   |  |
| 10.9.2 Power-frequency electric strength   |                  |   | Is the panel builder's responsibility.   |
| 10.9.3 Impulse withstand voltage   |                  |   | Is the panel builder's responsibility.   |
| 10.9.4 Testing of enclosures made of insulating material   |                  |   | Is the panel builder's responsibility.   |
| 10.10 Temperature rise   |                  |   | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating   |                  |   | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| 10.12 Electromagnetic compatibility  |                  |   | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| 10.13 Mechanical function  |                  |   | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.                         |

## Technical data ETIM 6.0

| Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation prot. (EC000228)   |    |  |                                   |
|--|----|--|-----------------------------------|
| Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss8.1-27-37-04-09 [AJZ716010]) |    |  |                                   |
| Rated permanent current I <sub>u</sub>   | A  |  | 400                               |
| Rated voltage  | V  |  | 690 - 690                         |
| Rated short-circuit breaking capacity I <sub>cu</sub> at 400 V, 50 Hz  | kA |  | 50                                |
| Overload release current setting   | A  |  | 200 - 400                         |
| Adjustment range short-term delayed short-circuit release  | A  |  | 400 - 4000                        |
| Adjustment range undelayed short-circuit release   | A  |  | 800 - 4400                        |
| Integrated earth fault protection  |    |  | No                                |
| Type of electrical connection of main circuit  |    |  | Screw connection                  |
| Device construction  |    |  | Built-in device plug-in technique |

|   |  |              |
|---|--|--------------|
| Suitable for DIN rail (top hat rail) mounting           |  | No           |
| DIN rail (top hat rail) mounting optional               |  | No           |
| Number of auxiliary contacts as normally closed contact |  | 0            |
| Number of auxiliary contacts as normally open contact   |  | 0            |
| Number of auxiliary contacts as change-over contact     |  | 0            |
| Switched-off indicator available                        |  | No           |
| With under voltage release                              |  | No           |
| Number of poles   |  | 3            |
| Position of connection for main current circuit         |  | Front side   |
| Type of control element                                 |  | Rocker lever |
| Complete device with protection unit                    |  | Yes          |
| Motor drive integrated                                  |  | No           |
| Motor drive optional                                    |  | Yes          |
| Degree of protection (IP)                               |  | IP20         |