



Part no. Article no. PKNM-32/1N/B/03-A-MW

236301

Similar to illustration

#### **Delivery program** Basic function Combined RCD/MCB devices 1 pole+N Number of poles В Tripping characteristic Application Switchgear for residential and commercial applications Rated current 32 I<sub>n</sub> А Rated switching capacity according to IEC/EN 61009 kΑ 10 Rated fault current А 0.3 $I_{\Delta N}$ Туре Type A Tripping А non-delayed PKNM Product range Sensitivity Pulse-current sensitive Impulse withstand current Partly surge-proof 250 A

# **Technical data**

### **Electrical**

Sensitivity	Pulse-current sensitive

## Design verification as per IEC/EN 61439

In	А	32
P <sub>vid</sub>	W	0
P <sub>vid</sub>	W	6.6
P <sub>vs</sub>	W	0
P <sub>diss</sub>	W	0
	°C	-25
	°C	40
		0
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Does not apply, since the entire switchgear needs to be evaluated.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Does not apply, since the entire switchgear needs to be evaluated.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
	P <sub>vid</sub> P <sub>vs</sub> P <sub>diss</sub>	P <sub>vid</sub> W P <sub>vid</sub> W P <sub>vs</sub> W P <sub>diss</sub> W °C °C

10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

# **Technical data ETIM 6.0**

Circuit breakers and fuses (EG000020) / Earth leakage circuit breaker (EC000905)

Electric engineering, automation, process control engineering / Electrical installatio [AFZ810012])	n, device / Residual cur	rrent protection system / MCB/RCCB combination (ecl@ss8.1-27-14-22-07
Number of poles (total)		2
Number of protected poles		1
Nominal rated voltage	V	230
Nominal rated current	А	32
Rated fault current	А	0.3
Leakage current type		Α
Current limiting class		3
Rated short-circuit breaking capacity EN 60898	kA	10
Rated short-circuit breaking capacity IEC 60947-2	kA	0
Frequency		50 Hz
Release characteristic		В
Concurrently switching N-neutral		Yes
Over voltage category		3
Pollution degree		2
Width in number of modular spacings		2
Built-in depth	mm	70
Suitable for flush-mounted installation		No
Degree of protection (IP)		IP20
Surge current capacity	kA	0.25
Voltage type		AC
Antinuisance tripping version		No