

https://www.phoenixcontact.com/us/products/2701450



Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



Axioline F, Digital input module, Digital inputs: 64, 24 V DC, connection technology: 1-conductor, transmission speed in the local bus: 100 Mbps, degree of protection: IP20, including bus base module and Axioline F connectors

## Product description

The module is designed for use within an Axioline F station. It is used to acquire digital signals. You can adjust the filter times of the inputs to increase noise immunity. Filter times of 100 µs enable you to implement a counter function with a maximum input frequency of 5 kHz in the application.

## Your advantages

- 64 digital inputs in accordance with EN 61131-2 type 1 and type 3
- 24 V DC, 2.4 mA
- · Connection of sensors in 1-conductor technology
- Minimum update time of < 100 μs
- Filter times can be adjusted in three increments: < 100  $\mu$ s, 1000  $\mu$ s or 3000  $\mu$ s
- · Maximum input frequency: 5 kHz
- · Device rating plate stored

### Commercial data

Item number	2701450
Packing unit	1 pc
Minimum order quantity	1 pc
Sales key	DR02
Product key	DRI231
Catalog page	Page 75 (C-6-2019)
GTIN	4046356753746
Weight per piece (including packing)	299 g
Weight per piece (excluding packing)	254 g
Customs tariff number	85389091
Country of origin	DE



https://www.phoenixcontact.com/us/products/2701450



## Technical data

### Dimensions

Dimensional drawing	53,6
Width	53.6 mm
Height	129.9 mm
Depth	54 mm
Note on dimensions	The depth applies when a TH 35-7.5 DIN rail is used (in accordance with EN 60715).

### Interfaces

### Axioline F local bus

Number of interfaces	2
Connection method	Bus base module
Transmission speed	100 Mbps

## System properties

#### Module

Input address area	8 Byte
Output address area	0 Byte
Required parameter data	3 Byte
Required configuration data	6 Byte

### Input data

### Digital

Input name	Digital inputs
Description of the input	EN 61131-2 types 1 and 3
Number of inputs	64
Connection method	Push-in connection
Connection technology	1-conductor
Input voltage range "0" signal	-3 V DC 5 V DC
Input voltage range "1" signal	11 V DC 30 V DC
Nominal input voltage U <sub>IN</sub>	24 V DC
Nominal input current at U <sub>IN</sub>	2.4 mA
Input filter time	3000 μs (Default)
	1000 μs
	< 100 µs



https://www.phoenixcontact.com/us/products/2701450

Conductor connection

Connection method

Conductor cross section rigid
Conductor cross section flexible

Conductor cross section AWG



Protective circuit	Polarity reversal protection of the inputs; parallel diode (30 V, 5 s
roduct properties	
Туре	block modular
Product type	I/O component
Product family	Axioline F
Mounting position	any (no temperature derating)
Scope of delivery	including bus base module and Axioline F connectors
Diagnostics messages	I/O supply failure yes
lectrical properties	
Potentials: Axioline F local bus supply (U <sub>Bus</sub> )	
Supply voltage	5 V DC (via bus base module)
Current draw	max. 120 mA (up to HW 01)
	max. 60 mA (from HW 02)
Power consumption	max. 600 mW (up to HW 01)
	max. 300 mW (from HW 02)
Potentials: Supply for digital input modules (U <sub>I</sub> )	
Supply voltage	24 V DC
Supply voltage range	19.2 V DC 30 V DC (including all tolerances, including ripple)
Current draw	max. 60 mA
Power consumption	max. 1.8 W
Protective circuit	Surge protection; electronic (35 V, 0.5 s)
	Reverse polarity protection; parallel diode; with external 5 A fuse (only for commissioning)
Electrical isolation/isolation of the voltage ranges	
Test voltage: 5 V supply of the local bus $(U_{Bus})$ / 24 V supply (I/Os)	500 V AC, 50 Hz, 1 min.
Test voltage: 5 V supply of the local bus $(U_{\mbox{\footnotesize Bus}})$ / functional ground	500 V AC, 50 Hz, 1 min.
Test voltage: 24 V supply (I/O) / functional ground	500 V AC, 50 Hz, 1 min.
onnection data	
Connection technology	
Connection name	Axioline F connector
Note on the connection method	Please observe the information provided on conductor cross sections in the "Axioline F: system and installation" user manual.

Applications with UL approval: only use copper conductors.

Push-in connection
0.2 mm² ... 1.5 mm²

0.2 mm<sup>2</sup> ... 1.5 mm<sup>2</sup>

24 ... 16



https://www.phoenixcontact.com/us/products/2701450



Stripping length	8 mm
Axioline F connector	
Connection method	Push-in connection
Note on the connection method	Please observe the information provided on conductor cross sections in the "Axioline F: system and installation" user manual.
	Applications with UL approval: only use copper conductors.
Conductor cross section, rigid	0.2 mm² 1.5 mm²
Conductor cross section, flexible	0.2 mm² 1.5 mm²
Conductor cross section AWG	24 16
Stripping length	8 mm

#### Environmental and real-life conditions

#### Ambient conditions

Ambient temperature (operation)	-25 °C 60 °C
Degree of protection	IP20
Air pressure (operation)	70 kPa 106 kPa (up to 3000 m above sea level)
Air pressure (storage/transport)	70 kPa 106 kPa (up to 3000 m above sea level)
Ambient temperature (storage/transport)	-40 °C 85 °C
Permissible humidity (operation)	5 % 95 % (non-condensing)
Permissible humidity (storage/transport)	5 % 95 % (non-condensing)

## Standards and regulations

## Mounting

Mounting type	DIN rail mounting
Mounting position	any (no temperature derating)





2701450

https://www.phoenixcontact.com/us/products/2701450

## Classifications

UNSPSC 21.0

### **ECLASS**

	ECLASS-11.0	27242604		
	ECLASS-12.0	27242604		
	ECLASS-13.0	27242604		
ETIM				
	ETIM 9.0	EC001599		
UN	ISPSC			

32151600



https://www.phoenixcontact.com/us/products/2701450



## Environmental product compliance

REACh SVHC	Lead 7439-92-1
China RoHS	Environmentally Friendly Use Period = 50 years
	For information on hazardous substances, refer to the manufacturer's declaration available under "Downloads"

Phoenix Contact 2024 © - all rights reserved https://www.phoenixcontact.com

Phoenix Contact USA 586 Fulling Mill Road Middletown, PA 17057, United States (+717) 944-1300 info@phoenixcon.com