

https://www.phoenixcontact.com/us/products/2702053



Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



Axioline F, Digital output module, Digital outputs: 64, 24 V DC, 500 mA, connection technology: 1-conductor, transmission speed in the local bus: 100 Mbps, degree of protection: IP20, including bus base module and Axioline F connectors

## Product description

The module is designed for use within an Axioline F station. It is used to output digital signals. The outputs are protected against short circuit and overload.

## Your advantages

- · 64 digital outputs
- 24 V DC, 500 mA
- · Connection of actuators in 1-conductor technology
- Minimum update time of < 100 μs
- · Device rating plate stored

### Commercial data

Item number	2702053
Packing unit	1 pc
Minimum order quantity	1 pc
Sales key	DR02
Product key	DRI232
Catalog page	Page 109 (C-6-2017)
GTIN	4046356932486
Weight per piece (including packing)	302.4 g
Weight per piece (excluding packing)	260 g
Customs tariff number	85389091
Country of origin	DE



https://www.phoenixcontact.com/us/products/2702053



## Technical data

### **Dimensions**

Dimensional drawing	53,6
Width	53.6 mm
Height	129.9 mm
Depth	54 mm
Note on dimensions	The depth applies when a TH 35-7.5 DIN rail is used (in accordance with EN 60715).

### Interfaces

### Axioline F local bus

Number of interfaces	2
Connection method	Bus base module
Transmission speed	100 Mbps

## System properties

### Module

Input address area	0 Byte
Output address area	8 Byte
Required parameter data	1 Byte
Required configuration data	6 Byte

## Output data

### Digital

-	
Output name	Digital outputs
Connection method	Push-in connection
Connection technology	1-conductor
Number of outputs	64
Protective circuit	Short-circuit protection, overload protection of the outputs; electronic
Output voltage	24 V
Limitation of the voltage induced on circuit interruption	-25.8 V15 V
Maximum output current per module	16 A (provide external protection)
Nominal output voltage	24 V DC
Load min.	10 kΩ
Output voltage when switched off	max. 1 V



https://www.phoenixcontact.com/us/products/2702053



Output current when switched off	max. 300 μA
Nominal load, inductive	max. 12 VA (1.2 H, 48 Ω, with nominal voltage)
Nominal load, lamp	max. 12 W (at nominal voltage)
Nominal load, ohmic	max. 12 W (48 $\Omega$ , with nominal voltage)
Switching frequency	max. 10000 per second (with ohmic load)
	max. 1 per second (with inductive load)
	max. 16 per second (with nominal lamp load)
Reverse voltage resistance to short pulses	limited protection up to 0.5 A for 1 s
Behavior with overload	Shutdown with automatic restart
Behavior with inductive overload	Output can be destroyed
Signal delay	max. 100 μs (when switched on)
	max. 100 µs (during switching off with ohmic nominal load)
Overcurrent shut-down	as of 0.7 A
Output current with ground connection interrupt when switched off	< 1 mA
Output name	Digital outputs
Connection method	Push-in connection
Connection technology	1-conductor
Number of outputs	64
Protective circuit	Short-circuit protection, overload protection of the outputs; electronic
Output voltage	24 V
Limitation of the voltage induced on circuit interruption	-25.8 V15 V
Maximum output current per module	16 A (provide external protection)
Nominal output voltage	24 V DC
Load min.	10 kΩ
Output voltage when switched off	max. 1 V
Output current when switched off	max. 300 μA
Nominal load, inductive	max. 12 VA (1.2 H, 48 Ω, with nominal voltage)
Nominal load, lamp	max. 12 W (at nominal voltage)
Nominal load, ohmic	max. 12 W (48 Ω, with nominal voltage)
Switching frequency	max. 10000 per second (with ohmic load)
	max. 1 per second (with inductive load)
	max. 16 per second (with nominal lamp load)
Reverse voltage resistance to short pulses	limited protection up to 0.5 A for 1 s
Behavior with overload	Shutdown with automatic restart
Behavior with inductive overload	Output can be destroyed
Signal delay	max. 100 μs (when switched on)
	max. 100 µs (during switching off with ohmic nominal load)
Overcurrent shut-down	as of 0.7 A
Output current with ground connection interrupt when switched off	< 1 mA

### Product properties

Туре	block modular
------	---------------



https://www.phoenixcontact.com/us/products/2702053



Product type	I/O component
Product family	Axioline F
Mounting position	any (no temperature derating)
Scope of delivery	including bus base module and Axioline F connectors
Insulation characteristics	
Overvoltage category	II (IEC 60664-1, EN 60664-1)
Pollution degree	2 (IEC 60664-1, EN 60664-1)
ectrical properties	
Maximum power dissipation for nominal condition	2.4 W
Potentials: Axioline F local bus supply (U <sub>Bus</sub> )	
Supply voltage	5 V DC (via bus base module)
Current draw	max. 120 mA (up to HW 02)
	max. 60 mA (from HW 03)
Power consumption	max. 600 mW (up to HW 02)
	max. 300 mW (from HW 03)
Potentials: Supply for digital output modules ( $U_{\Omega}$ )	
Supply voltage	24 V DC
Supply voltage range	19.2 V DC 30 V DC (including all tolerances, including ripple)
Current draw	max. 16 A (Provide external protection; if the total current of 8 A is exceeded, connect the supply at the power connector parallel via both terminal points.)
Power consumption	max. 480 W (of which 1.8 W internal losses)
Protective circuit	Surge protection; electronic (35 V, 0.5 s)
	Reverse polarity protection; parallel diode; with external 5 A fuse (only for commissioning)
Electrical isolation/isolation of the voltage ranges	
Test voltage: 5 V supply of the local bus (U <sub>Bus</sub> ) / 24 V supply (I/Os)	500 V AC, 50 Hz, 1 min.
Test voltage: 5 V supply of the local bus $(U_{\text{Bus}})$ / functional ground	500 V AC, 50 Hz, 1 min.

#### Connection data

### Connection technology

Connection name	Axioline F connector
Note on the connection method	Please observe the information provided on conductor cross sections in the "Axioline F: system and installation" user manual.

#### Conductor connection

Conductor Connection	
Connection method	Push-in connection
Conductor cross section rigid	0.2 mm <sup>2</sup> 1.5 mm <sup>2</sup>
Conductor cross section flexible	0.2 mm² 1.5 mm²
Conductor cross section AWG	24 16



https://www.phoenixcontact.com/us/products/2702053



Stripping length	8 mm
Axioline F connector	
Connection method	Push-in connection
Note on the connection method	Please observe the information provided on conductor cross sections in the "Axioline F: system and installation" user manual.
Conductor cross section, rigid	0.2 mm² 1.5 mm²
Conductor cross section, flexible	0.2 mm² 1.5 mm²
Conductor cross section AWG	24 16
Stripping length	8 mm

### Environmental and real-life conditions

### Ambient conditions

Ambient temperature (operation)	-25 °C 60 °C
Degree of protection	IP20
Air pressure (operation)	70 kPa 106 kPa (up to 3000 m above sea level)
Air pressure (storage/transport)	70 kPa 106 kPa (up to 3000 m above sea level)
Ambient temperature (storage/transport)	-40 °C 85 °C
Permissible humidity (operation)	5 % 95 % (non-condensing)
Permissible humidity (storage/transport)	5 % 95 % (non-condensing)

## Standards and regulations

## Mounting

Mounting type	DIN rail mounting
Mounting position	any (no temperature derating)



2702053

https://www.phoenixcontact.com/us/products/2702053

## Classifications

UNSPSC 21.0

### **ECLASS**

ECLASS-11.0	27242604
ECLASS-12.0	27242604
ECLASS-13.0	27242604
ETIM	
ETIM 9.0	EC001599
UNSPSC	

32151600



https://www.phoenixcontact.com/us/products/2702053



## Environmental product compliance

REACh SVHC	Lead 7439-92-1
China RoHS	Environmentally Friendly Use Period = 50 years
	For information on hazardous substances, refer to the manufacturer's declaration available under "Downloads"

Phoenix Contact 2024 © - all rights reserved https://www.phoenixcontact.com

Phoenix Contact USA 586 Fulling Mill Road Middletown, PA 17057, United States (+717) 944-1300 info@phoenixcon.com