#### 3273078

https://www.phoenixcontact.com/us/products/3273078

**PHŒNIX** CONTACT

Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



Distribution block, Block with vertical alignment and integrated supply, nom. voltage: 690 V, nominal current: 24 A, number of connections: 7, connection method: Push-in connection, Load contact, cross section: 0.14 mm<sup>2</sup> - 4 mm<sup>2</sup>, Push-in connection, Line contact, Rated cross section: 6 mm<sup>2</sup>, cross section: 0.5 mm<sup>2</sup> - 10 mm<sup>2</sup>, mounting type: NS 35/7,5, NS 35/15, color: white

### Your advantages

- · Flexible use, thanks to DIN rail mounting, direct mounting or adhesive mounting
- · Clear wiring, thanks to eleven different color variants
- · Time-saving conductor connection, thanks to tool-free Push-in direct connection technology
- · Time savings of up to 80 %, thanks to ready-to-mount blocks without manual bridging
- · Space savings of up to 50 % on the DIN rail, thanks to transverse mounting

### Commercial data

| Item number                          | 3273078             |
|--------------------------------------|---------------------|
| Packing unit                         | 10 pc               |
| Minimum order quantity               | 10 pc               |
| Sales key                            | BE09                |
| Product key                          | BEA122              |
| Catalog page                         | Page 445 (C-1-2019) |
| GTIN                                 | 4055626390956       |
| Weight per piece (including packing) | 24.28 g             |
| Weight per piece (excluding packing) | 24.28 g             |
| Customs tariff number                | 85369010            |
| Country of origin                    | PL                  |

3273078

https://www.phoenixcontact.com/us/products/3273078



### Technical data

#### Notes

| General | the blocks can be bridged with one another via the conductor shaft, for corresponding plug-in bridges, see accessories   |
|---------|--|
| General |  |
| Note    | The maximum load current of a single clamping unit must not be exceeded.   |
|         | For power distribution applications, IEC 60364-4-43.2008;<br>modified + corrigendum Okt. 2008 (DIN VDE 0100-430:2010-10)<br>section 433.2 ff must be observed! |

#### **Product properties**

| Product type              | Distributor terminal block |
|---------------------------|----------------------------|
| Number of connections     | 7                          |
| Number of rows            | 1                          |
| Potentials                | 1                          |
| nsulation characteristics |                            |
| Overvoltage category      | III                        |
|                           |                            |

#### Electrical properties

| Rated surge voltage                             | 8 kV   |
|---|--------|
| Maximum power dissipation for nominal condition | 0.77 W |

### Connection data

| Service Entrance                | yes                 |
|---------------------------------|---------------------|
| Number of connections per level | 7                   |
| Nominal cross section           | 2.5 mm <sup>2</sup> |
| Rated cross section AWG         | 14                  |

Load contact

| Stripping length  | 8 mm 10 mm   |
|---|--|
| Internal cylindrical gage   | A3   |
| Connection in acc. with standard                                  | IEC 60947-7-1  |
| Conductor cross section rigid                                     | 0.14 mm <sup>2</sup> 4 mm <sup>2</sup>                 |
| Cross section AWG   | 26 12 (converted acc. to IEC)                          |
| Conductor cross section flexible                                  | 0.14 mm <sup>2</sup> 2.5 mm <sup>2</sup>               |
| Conductor cross section, flexible [AWG]                           | 26 14 (converted acc. to IEC)                          |
| Conductor cross-section flexible (ferrule without plastic sleeve) | 0.14 mm <sup>2</sup> 2.5 mm <sup>2</sup>               |
| Flexible conductor cross section (ferrule with plastic sleeve)    | 0.14 mm <sup>2</sup> 2.5 mm <sup>2</sup>               |
| Nominal current   | 24 A   |
| Maximum load current  | 32 A (with 4 mm <sup>2</sup> conductor cross section)  |
| Maximum total current   | 57 A (with 10 mm <sup>2</sup> conductor cross section) |



#### 3273078

https://www.phoenixcontact.com/us/products/3273078

| Nominal voltage   | 690 V   |
|---|---|
|   |   |
|   | (a) (a)   |
| Stripping length  | 10 mm 12 mm   |
| Internal cylindrical gage   | A3  |
| Connection in acc. with standard  | IEC 60947-7-1   |
| Conductor cross section rigid   | 0.5 mm <sup>2</sup> 10 mm <sup>2</sup>  |
| Cross section AWG   | 26 12 (converted acc. to IEC)   |
| Conductor cross section flexible  | 0.5 mm <sup>2</sup> 10 mm <sup>2</sup>  |
| Conductor cross section, flexible [AWG]   | 26 14 (converted acc. to IEC)   |
| Conductor cross-section flexible (ferrule without plastic sleeve)   | 0.5 mm <sup>2</sup> 6 mm <sup>2</sup>   |
| Flexible conductor cross section (ferrule with plastic sleeve)  | 0.5 mm <sup>2</sup> 6 mm <sup>2</sup>   |
| 2 conductors with the same cross section, flexible, with TWIN ferrule with plastic sleeve   | 0.5 mm² 1.5 mm²   |
| Nominal current   | 41 A (with 6 mm <sup>2</sup> conductor cross section)   |
| Maximum load current  | 57 A (with 10 mm <sup>2</sup> conductor cross section)  |
| Maximum total current   | 57 A  |
| Nominal voltage   | 690 V   |
| Nominal cross section   | 6 mm <sup>2</sup>   |
| _oad contact Connection cross sections directly pluggable   |   |
| Conductor cross section rigid   | 0.34 mm <sup>2</sup> 4 mm <sup>2</sup>  |
| Conductor cross section, rigid [AWG]  | 24 12 (converted acc. to IEC)   |
| Conductor cross-section flexible (ferrule without plastic sleeve)   | 0.5 mm² 2.5 mm²   |
|   | 0.5 11111 2.5 11111   |
| Flexible conductor cross section (ferrule with plastic sleeve)  | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup>  |
| Flexible conductor cross section (ferrule with plastic sleeve)  |   |
| Flexible conductor cross section (ferrule with plastic sleeve)<br>ine contact Connection cross sections directly pluggable  | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup>  |
| Flexible conductor cross section (ferrule with plastic sleeve)<br>Line contact Connection cross sections directly pluggable<br>Conductor cross section rigid  | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup>  |
| Flexible conductor cross section (ferrule with plastic sleeve)         Line contact Connection cross sections directly pluggable         Conductor cross section rigid         Conductor cross-section flexible (ferrule without plastic sleeve)  | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup>   |
| Flexible conductor cross section (ferrule with plastic sleeve)<br>Line contact Connection cross sections directly pluggable<br>Conductor cross section rigid  | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup>  |
| Flexible conductor cross section (ferrule with plastic sleeve)         Line contact Connection cross sections directly pluggable         Conductor cross section rigid         Conductor cross-section flexible (ferrule without plastic sleeve)  | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup>   |
| Flexible conductor cross section (ferrule with plastic sleeve)         Line contact Connection cross sections directly pluggable         Conductor cross section rigid         Conductor cross-section flexible (ferrule without plastic sleeve)         Flexible conductor cross section (ferrule with plastic sleeve)   | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup>   |
| Flexible conductor cross section (ferrule with plastic sleeve)         Line contact Connection cross sections directly pluggable         Conductor cross section rigid         Conductor cross-section flexible (ferrule without plastic sleeve)         Flexible conductor cross section (ferrule with plastic sleeve)         mensions  | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup>                                  |
| Flexible conductor cross section (ferrule with plastic sleeve)         Line contact Connection cross sections directly pluggable         Conductor cross section rigid         Conductor cross-section flexible (ferrule without plastic sleeve)         Flexible conductor cross section (ferrule with plastic sleeve)         Flexible conductor cross section (ferrule with plastic sleeve)         mensions         Width   | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>28.6 mm                       |
| Flexible conductor cross section (ferrule with plastic sleeve)         Line contact Connection cross sections directly pluggable         Conductor cross section rigid         Conductor cross-section flexible (ferrule without plastic sleeve)         Flexible conductor cross section (ferrule with plastic sleeve)         Flexible conductor cross section (ferrule with plastic sleeve)         Width         Height   | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>28.6 mm<br>58.1 mm            |
| Flexible conductor cross section (ferrule with plastic sleeve)         Line contact Connection cross sections directly pluggable         Conductor cross section rigid         Conductor cross-section flexible (ferrule without plastic sleeve)         Flexible conductor cross section (ferrule with plastic sleeve)         Flexible conductor cross section (ferrule with plastic sleeve)         Width         Height         Depth on NS 15  | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>28.6 mm<br>58.1 mm<br>30.4 mm |
| Flexible conductor cross section (ferrule with plastic sleeve)<br>Line contact Connection cross sections directly pluggable<br>Conductor cross section rigid<br>Conductor cross-section flexible (ferrule without plastic sleeve)<br>Flexible conductor cross section (ferrule with plastic sleeve)<br>mensions<br>Width<br>Height<br>Depth on NS 15<br>Depth on NS 35/7,5  | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>28.6 mm<br>58.1 mm<br>30.4 mm |
| Flexible conductor cross section (ferrule with plastic sleeve) Line contact Connection cross sections directly pluggable Conductor cross section rigid Conductor cross section flexible (ferrule without plastic sleeve) Flexible conductor cross section (ferrule with plastic sleeve) Flexible conductor cross section (ferrule with plastic sleeve) Width Height Depth on NS 15 Depth on NS 35/7,5 Atterial specifications   | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>28.6 mm<br>58.1 mm<br>30.4 mm<br>32.4 mm                             |
| Flexible conductor cross section (ferrule with plastic sleeve) Line contact Connection cross sections directly pluggable Conductor cross section rigid Conductor cross-section flexible (ferrule without plastic sleeve) Flexible conductor cross section (ferrule with plastic sleeve) Flexible conductor cross section (ferrule with plastic sleeve) Width Height Depth on NS 15 Depth on NS 35/7,5 Herial specifications Color   | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>28.6 mm<br>58.1 mm<br>30.4 mm<br>32.4 mm                             |
| Flexible conductor cross section (ferrule with plastic sleeve)         Line contact Connection cross sections directly pluggable         Conductor cross section rigid         Conductor cross section flexible (ferrule without plastic sleeve)         Flexible conductor cross section (ferrule with plastic sleeve)         Flexible conductor cross section (ferrule with plastic sleeve)         Flexible conductor cross section (ferrule with plastic sleeve)         Width         Height         Depth on NS 15         Depth on NS 35/7,5         Aterial specifications         Color         Flammability rating according to UL 94  | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>28.6 mm<br>58.1 mm<br>30.4 mm<br>32.4 mm                             |
| Flexible conductor cross section (ferrule with plastic sleeve)   Line contact Connection cross sections directly pluggable   Conductor cross section rigid   Conductor cross-section flexible (ferrule without plastic sleeve)   Flexible conductor cross section (ferrule with plastic sleeve)   Flexible conductor cross section (ferrule with plastic sleeve)   Width   Height   Depth on NS 15   Depth on NS 35/7,5   Color   Flammability rating according to UL 94   Insulating material group  | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>28.6 mm<br>58.1 mm<br>30.4 mm<br>32.4 mm<br>white<br>V0<br>1         |
| Flexible conductor cross section (ferrule with plastic sleeve)         Line contact Connection cross sections directly pluggable         Conductor cross section rigid         Conductor cross section flexible (ferrule without plastic sleeve)         Flexible conductor cross section (ferrule with plastic sleeve)         Width         Height         Depth on NS 15         Depth on NS 35/7,5         Aterial specifications         Color         Flammability rating according to UL 94         Insulating material group         Insulating material | 0.34 mm <sup>2</sup> 2.5 mm <sup>2</sup><br>1 mm <sup>2</sup> 10 mm <sup>2</sup><br>1 mm <sup>2</sup> 6 mm <sup>2</sup><br>28.6 mm<br>58.1 mm<br>30.4 mm<br>32.4 mm<br>white<br>V0<br>I<br>PA   |



#### 3273078

https://www.phoenixcontact.com/us/products/3273078

| Fire protection for rail vehicles (DIN EN 45545-2) R22  | HL 1 - HL 3 |
|---|-------------|
| Fire protection for rail vehicles (DIN EN 45545-2) R23  | HL 1 - HL 3 |
| Fire protection for rail vehicles (DIN EN 45545-2) R24  | HL 1 - HL 3 |
| Fire protection for rail vehicles (DIN EN 45545-2) R26  | HL 1 - HL 3 |
| Calorimetric heat release NFPA 130 (ASTM E 1354)        | 28 MJ/kg    |
| Surface flammability NFPA 130 (ASTM E 162)              | passed      |
| Specific optical density of smoke NFPA 130 (ASTM E 662) | passed      |
| Smoke gas toxicity NFPA 130 (SMP 800C)                  | passed      |

#### Electrical tests

| Requirement temperature-rise test       Increase in temperature ≤ 45 K         Result       Test passed         Short-time withstand current 6 mm²       0.72 kA         Short-time withstand current 10 mm²       1.2 kA         Result       Test passed         Power-frequency withstand voltage       Test passed         Power-frequency withstand voltage       1.89 kV         Result       Test passed         Power-frequency withstand voltage       Test passed         Power-frequency withstand voltage       1.89 kV         Result       Test passed         Power-frequency withstand voltage       No         Power-frequency withstand voltage       No         Power-frequency withstand voltage       Test passed         Mechanical tests       Test passed         Mechanical strength       Test passed         Attachment on the carrier       NS 35         DIN rait/fixing support       S N         Result       Test passed  | Test voltage setpoint                           | 9.8 kV   |
|---|---|--|
| Result       Test passed         Short-time withstand current 6 mm³       0.72 kA         Short-time withstand current 10 mm³       1.2 kA         Result       Test passed         Power-frequency withstand voltage       Test passed         Power-frequency withstand voltage       1.89 kV         Result       Test passed         Power-frequency withstand voltage       1.89 kV         Result       Test passed         echanical properties       Mechanical data         Open side panel       No         echanical tests       Mechanical strength         Result       Test passed         Attachment on the carrier       DIN rail/fixing support         DIN rail/fixing support       S 5         Result       Test passed         Note       When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks.         For versions with 6 or 7 connections, it is enough to place one DIN rail adapter underneath the connection point or a flange element between the blocks.  | Result  | Test passed  |
| Result       Test passed         Short-time withstand current 6 mm²       0.72 kA         Short-time withstand current 10 mm²       1.2 kA         Result       Test passed         Power-frequency withstand voltage       Test passed         Power-frequency withstand voltage       1.89 kV         Result       Test passed         Power-frequency withstand voltage       Test passed         Power-frequency withstand voltage       Test passed         Result       Test passed         echanical properties       Mechanical data         Open side panel       No         echanical strength       Result         Result       Test passed         Mechanical strength       Test passed         Attachment on the carrier       IN rail/fixing support         DIN rail/fixing support       NS 35         Test force setpoint       5 N         Result       Test passed         Note       When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks.         For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements   | Temperature-rise test                           |  |
| Short-time withstand current 10 mm²       0.72 kA         Short-time withstand current 10 mm²       1.2 kA         Result       Test passed         Power-frequency withstand voltage       1.89 kV         Test voltage setpoint       1.89 kV         Result       Test passed         Pechanical properties       Mechanical data         Open side panel       No         echanical tests       Mechanical strength         Result       Test passed         Attachment on the carrier       DIN rail/fixing support         DIN rail/fixing support       S 35         Test passed       S 10 km and apper underneath the connection point or a flange element between the blocks, it is recommended to either place a DIN rail adapter underneath the connection, it is enough to place one DIN rail adapter centrally per block and place flange elements  | Requirement temperature-rise test               | Increase in temperature ≤ 45 K   |
| Short-time withstand current 10 mm*       1.2 kA         Result       Test passed         Power-frequency withstand voltage       1.89 kV         Test voltage setpoint       1.89 kV         Result       Test passed         echanical properties       Mechanical data         Open side panel       No         echanical tests       Mechanical strength         Result       Test passed         Attachment on the carrier       DIN rail/fixing support         DIN rail/fixing support       S 35         Test passed       So N         Result       Test passed         Note       When aligning several blocks, it is recommended to either place a DIN rail dapter underneath the connection point or a flange element between the blocks, it is enough to place one DIN rail adapter centrally per block and place flange element between the blocks and place flange element between the block and place flange element betwe | Result  | Test passed  |
| Result       Test passed         Power-frequency withstand voltage       1.89 kV         Test voltage setpoint       1.89 kV         Result       Test passed         echanical properties         Mechanical data         Open side panel       No         echanical strength         Result       Test passed         Attachment on the carrier         DIN rail/fixing support       NS 35         Test force setpoint       5 N         Result       Test passed         Note       When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks.         For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements   | Short-time withstand current 6 mm <sup>2</sup>  | 0.72 kA  |
| Power-frequency withstand voltage Test voltage setpoint Test voltage setpoint Result Test passed  Attachment on the carrier DIN rail/fixing support Test force setpoint Note Note Note Note Note Note Note Not  | Short-time withstand current 10 mm <sup>2</sup> | 1.2 kA   |
| Test voltage setpoint       1.89 kV         Result       Test passed         echanical properties         Mechanical data         Open side panel       No         echanical tests         Mechanical strength         Result       Test passed         Attachment on the carrier         DIN rail/fixing support       NS 35         Test force setpoint       5 N         Result       Test passed         Note       When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks.         For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements   | Result  | Test passed  |
| Result       Test passed         echanical properties         Mechanical data         Open side panel       No         echanical tests         Mechanical strength         Result       Test passed         Attachment on the carrier         DIN rail/fixing support       NS 35         Test force setpoint       5 N         Result       Test passed         Note       When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks.         For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements   | Power-frequency withstand voltage               |  |
| echanical properties         Mechanical data         Open side panel       No         echanical tests         Mechanical strength         Result       Test passed         Attachment on the carrier         DIN rail/fixing support       NS 35         Test force setpoint       5 N         Result       Test passed         Note       When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks.         For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements  | Test voltage setpoint                           | 1.89 kV  |
| Mechanical data         Open side panel       No         echanical tests         Mechanical strength         Result       Test passed         Attachment on the carrier         DIN rail/fixing support       NS 35         Test force setpoint       5 N         Result       Test passed         Note       When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks.         For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements   | Result  | Test passed  |
| Attachment on the carrier         DIN rail/fixing support       NS 35         Test force setpoint       5 N         Result       Test passed         Note       When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks.         For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements   | echanical tests                                 |  |
| DIN rail/fixing support       NS 35         Test force setpoint       5 N         Result       Test passed         Note       When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks.         For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements   | Result  | Test passed  |
| Test force setpoint       5 N         Result       Test passed         Note       When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks.         For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements   | Attachment on the carrier                       |  |
| Result       Test passed         Note       When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks.         For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements   | DIN rail/fixing support                         | NS 35  |
| Note       When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks.         For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements  |   |  |
| a DIN rail adapter underneath the connection point or a flange<br>element between the blocks.For versions with 6 or 7 connections, it is enough to place one<br>DIN rail adapter centrally per block and place flange elements  |   | 5 N  |
| DIN rail adapter centrally per block and place flange elements  | Test force setpoint                             |  |
|   | Test force setpoint<br>Result                   | Test passed<br>When aligning several blocks, it is recommended to either place<br>a DIN rail adapter underneath the connection point or a flange |

When using the DIN rail adapter PTFIX-NS35, an aligned block must not protrude by more than a half.



#### 3273078

https://www.phoenixcontact.com/us/products/3273078

| Rotation speed   | 10 rpm            |
|--|-------------------|
| Revolutions  | 135               |
| Conductor cross section/weight                             | 0.5 mm² / 0.3 kg  |
|  | 6 mm² / 1.4 kg    |
|  | 10 mm² / 2 kg     |
| Result   | Test passed       |
| Test for conductor damage and slackening<br>Rotation speed | 10 rpm            |
| Revolutions  | 135               |
| Conductor cross section/weight                             | 0.14 mm² / 0.2 kg |
|  | 2.5 mm² / 0.7 kg  |
|  | 4 mm² / 0.9 kg    |
|  |                   |

#### Environmental and real-life conditions

| Femperature cycles             | 192   |
|--------------------------------|---|
| Result                         | Test passed                                   |
| eedle-flame test               |   |
| Time of exposure               | 30 s  |
| Result                         | Test passed                                   |
| scillation/broadband noise     |   |
| Specification                  | DIN EN 50155 (VDE 0115-200):2008-03           |
| Spectrum                       | Service life test category 2, bogie-mounted   |
| Frequency                      | $f_1 = 5 \text{ Hz to } f_2 = 250 \text{ Hz}$ |
| ASD level                      | 6.12 (m/s <sup>2</sup> ) <sup>2</sup> /Hz     |
| Acceleration                   | 3.12g   |
| Test duration per axis         | 5 h   |
| Test directions                | X-, Y- and Z-axis                             |
| Result                         | Test passed                                   |
| hocks                          |   |
| Specification                  | DIN EN 50155 (VDE 0115-200):2008-03           |
| Pulse shape                    | Half-sine                                     |
| Acceleration                   | 30g   |
| Shock duration                 | 18 ms   |
| Number of shocks per direction | 3   |
| Test directions                | X-, Y- and Z-axis (pos. and neg.)             |
| Result                         | Test passed                                   |

#### 3273078

https://www.phoenixcontact.com/us/products/3273078

| Ambient temperature (operation)          | -60 °C 110 °C (Operating temperature range incl. self-heating; for max. short-term operating temperature, see RTI Elec.) |
|--|--|
| Ambient temperature (storage/transport)  | -25 °C 60 °C (for a short time, no longer than 24 h, -60°C to +70°C)   |
| Ambient temperature (assembly)           | -5 °C 70 °C  |
| Ambient temperature (actuation)          | -5 °C 70 °C  |
| Permissible humidity (operation)         | 20 % 90 %  |
| Permissible humidity (storage/transport) | 30 % 70 %  |
| andards and regulations                  |  |
| anualus anu regulations                  |  |
| Connection in acc. with standard         | IEC 60947-7-1  |

| Mounting type | NS 35/7,5 |
|---------------|-----------|
|               | NS 35/15  |

**PHŒNIX** CONTACT 3273078

https://www.phoenixcontact.com/us/products/3273078



## Classifications

#### ECLASS

|        | ECLASS-11.0 | 27141120 |  |  |
|--------|-------------|----------|--|--|
|        | ECLASS-13.0 | 27250118 |  |  |
| ETIM   |             |          |  |  |
|        | ETIM 9.0    | EC000897 |  |  |
| UNSPSC |             |          |  |  |
|        | UNSPSC 21.0 | 39121400 |  |  |

3273078

https://www.phoenixcontact.com/us/products/3273078

### **PHŒNIX** CONTACT

### Environmental product compliance

| China RoHS | Environmentally friendly use period: unlimited = EFUP-e |
|------------|---|
|            | No hazardous substances above threshold values          |

Phoenix Contact 2024 © - all rights reserved https://www.phoenixcontact.com

Phoenix Contact USA 586 Fulling Mill Road Middletown, PA 17057, United States (+717) 944-1300 info@phoenixcon.com