

3273420

https://www.phoenixcontact.com/us/products/3273420

Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



Distribution block, Basic terminal block, nom. voltage: 450 V, nominal current: 24 A, number of connections: 12, connection method: Push-in connection, cross section: $0.14~\text{mm}^2$ - $4~\text{mm}^2$, mounting type: adhesive, color: red

Your advantages

- Time savings of up to 80 %, thanks to ready-to-mount blocks without manual bridging
- · Time-saving conductor connection, thanks to tool-free Push-in direct connection technology
- Space savings of up to 50 % on the DIN rail, thanks to transverse mounting
- · Flexible use, thanks to DIN rail mounting, direct mounting or adhesive mounting
- · Clear wiring, thanks to eleven different color variants

Commercial data

Item number	3273420
Packing unit	8 pc
Minimum order quantity	8 pc
Sales key	BE09
Product key	BEA114
Catalog page	Page 440 (C-1-2019)
GTIN	4055626392837
Weight per piece (including packing)	23.7 g
Weight per piece (excluding packing)	23.7 g
Customs tariff number	85369010
Country of origin	PL



https://www.phoenixcontact.com/us/products/3273420



Technical data

Notes

General	the blocks can be bridged with one another via the conductor shaft, for corresponding plug-in bridges, see accessories
General	
Note	The maximum load current of a single clamping unit must not be exceeded.

Product properties

Product type	Distributor terminal block	
Number of connections	12	
Number of rows	1	
Potentials	1	
Insulation characteristics		
Overvoltage category	III	
Degree of pollution	3	

Electrical properties

Rated surge voltage	6 kV
Maximum power dissipation for nominal condition	0.77 W

Connection data

Number of connections per level	12
Nominal cross section	2.5 mm ²
Rated cross section AWG	12
Stripping length	8 mm 10 mm
Internal cylindrical gage	A3
Connection in acc. with standard	IEC 60998-2-2
Conductor cross section rigid	0.14 mm² 4 mm²
Cross section AWG	26 12 (converted acc. to IEC)
Conductor cross section flexible	0.14 mm² 2.5 mm²
Conductor cross section, flexible [AWG]	26 14 (converted acc. to IEC)
Conductor cross-section flexible (ferrule without plastic sleeve)	0.14 mm² 2.5 mm²
Flexible conductor cross section (ferrule with plastic sleeve)	0.14 mm² 2.5 mm²
Nominal current	24 A
Maximum load current	32 A
Maximum total current	48 A
Nominal voltage	450 V

Connection cross sections directly pluggable

· · · · · · · · · · · · · · · · · · ·	
Conductor cross section rigid	0.34 mm² 4 mm²
Conductor cross section, rigid [AWG]	24 12 (converted acc. to IEC)



3273420

Frequency

ASD level

Acceleration

https://www.phoenixcontact.com/us/products/3273420

Conductor cross-section flexible (ferrule without plastic sleeve)	0.34 mm² 2.5 mm²
Flexible conductor cross section (ferrule with plastic sleeve)	0.34 mm² 2.5 mm²
mensions	
Width	31.5 mm
Height	28.6 mm
Depth	22.7 mm
aterial specifications	
Color	red
Flammability rating according to UL 94	V0
Insulating material group	I
Insulating material	PA
Static insulating material application in cold	-60 °C
Temperature index of insulation material (DIN EN 60216-1 (VDE 0304-21))	125 °C
Relative insulation material temperature index (Elec., UL 746 B)	125 °C
Mechanical data Open side panel	No
Open side panel echanical tests	No
Open side panel echanical tests Attachment on the carrier	
Open side panel echanical tests Attachment on the carrier Result	Test passed
Open side panel echanical tests Attachment on the carrier	Test passed
Open side panel echanical tests Attachment on the carrier Result	Test passed When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange
Open side panel echanical tests Attachment on the carrier Result	Test passed When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks. For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements after every other block.
Open side panel echanical tests Attachment on the carrier Result	Test passed When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks. For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements after every other block. When using the DIN rail adapter PTFIX-NS35, an aligned block
Open side panel echanical tests Attachment on the carrier Result Note vironmental and real-life conditions	Test passed When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks. For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements after every other block. When using the DIN rail adapter PTFIX-NS35, an aligned block
Open side panel echanical tests Attachment on the carrier Result Note vironmental and real-life conditions Needle-flame test	Test passed When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks. For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements after every other block. When using the DIN rail adapter PTFIX-NS35, an aligned block must not protrude by more than a half.
Open side panel echanical tests Attachment on the carrier Result Note vironmental and real-life conditions Needle-flame test Time of exposure	Test passed When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks. For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements after every other block. When using the DIN rail adapter PTFIX-NS35, an aligned block must not protrude by more than a half.
Open side panel echanical tests Attachment on the carrier Result Note vironmental and real-life conditions Needle-flame test	Test passed When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks. For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements after every other block. When using the DIN rail adapter PTFIX-NS35, an aligned block must not protrude by more than a half.
Open side panel echanical tests Attachment on the carrier Result Note vironmental and real-life conditions Needle-flame test Time of exposure	Test passed When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks. For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements after every other block. When using the DIN rail adapter PTFIX-NS35, an aligned block must not protrude by more than a half.
Open side panel echanical tests Attachment on the carrier Result Note vironmental and real-life conditions Needle-flame test Time of exposure Result	Test passed When aligning several blocks, it is recommended to either place a DIN rail adapter underneath the connection point or a flange element between the blocks. For versions with 6 or 7 connections, it is enough to place one DIN rail adapter centrally per block and place flange elements after every other block. When using the DIN rail adapter PTFIX-NS35, an aligned block must not protrude by more than a half.

 $f_1 = 5 \text{ Hz to } f_2 = 250 \text{ Hz}$

 $6.12 (m/s^2)^2/Hz$

3.12g



3273420

https://www.phoenixcontact.com/us/products/3273420

Test duration per axis	5 h
Test directions	X-, Y- and Z-axis
Result	Test passed
hocks	
Specification	DIN EN 50155 (VDE 0115-200):2008-03
Pulse shape	Half-sine
Acceleration	30g
Shock duration	18 ms
Number of shocks per direction	3
Test directions	X-, Y- and Z-axis (pos. and neg.)
Result	Test passed
mbient conditions Ambient temperature (operation)	-35 °C 110 °C (Operating temperature range incl. self-heating for max. short-term operating temperature, see RTI Elec.)
Ambient temperature (storage/transport)	-25 °C 60 °C (for a short time, no longer than 24 h, -60 °C to +70 °C)
Ambient temperature (assembly)	-5 °C 70 °C
Ambient temperature (actuation)	-5 °C 70 °C
Permissible humidity (operation)	20 % 90 %
Permissible humidity (storage/transport)	30 % 70 %
ndards and regulations	
Connection in acc. with standard	IEC 60998-2-2
unting	
Mounting type	adhesive
3 VP3	333



3273420

https://www.phoenixcontact.com/us/products/3273420

Classifications

ECLASS

	ECLASS-11.0	27141120
	ECLASS-13.0	27250118
ΕΊ	ГІМ	
	ETIM 9.0	EC000897
UNSPSC		
	UNSPSC 21.0	39121400



3273420

https://www.phoenixcontact.com/us/products/3273420

Environmental product compliance

China RoHS	Environmentally friendly use period: unlimited = EFUP-e
	No hazardous substances above threshold values

Phoenix Contact 2024 © - all rights reserved https://www.phoenixcontact.com

Phoenix Contact USA 586 Fulling Mill Road Middletown, PA 17057, United States (+717) 944-1300 info@phoenixcon.com