

2864422

https://www.phoenixcontact.com/us/products/2864422

Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



MCR repeater power supplies, screw connection, input signal: (0)4..20 mA, output signal: (0)4.. 20 mA

Product description

The 6.2 mm wide MINI MCR-SL-RPS-I-I... repeater power supply supplies transmitters in the field and electrically isolates the input signal from the output signal. The module can be used in both isolator and repeater power supply operation.

Electrically isolated 0...20 mA or 4...20 mA analog standard signals are available on the input and output side.

The power supply (19.2 V DC to 30 V DC) can be supplied via connection terminal blocks on the modules or in conjunction with the DIN rail connector.

Your advantages

- Power supply possible via the foot element (TBUS)
- · Can be used as an isolator with passive input
- · Highly-compact repeater power supplies for electrical isolation, amplification, and filtering of standard analog signals
- · 3-way isolation
- · Supply of 2-conductor and passive 3-conductor sensors

Commercial data

Item number	2864422
Packing unit	1 pc
Minimum order quantity	1 pc
Sales key	C403
Product key	CK1211
Catalog page	Page 99 (C-7-2015)
GTIN	4017918956165
Weight per piece (including packing)	88.56 g
Weight per piece (excluding packing)	72 g
Customs tariff number	85437090
Country of origin	DE



2864422

https://www.phoenixcontact.com/us/products/2864422

Technical data

Notes

EMC note	EMC: class A product, see manufacturer's declaration in the download area
duct properties	
Product type	Repeater power supplies
Product family	MINI Analog
No. of channels	1
nsulation characteristics	
Overvoltage category	II
Pollution degree	2
ctrical properties	
Electrical isolation	3-way isolation
Electrical isolation between input and output	yes
Limit frequency (3 dB)	approx. 100 Hz
Maximum power dissipation for nominal condition	508 mW (24 V DC)
	208 mW (24 V DC)
Protective circuit	Transient protection
Signal transmission behavior	In = Out
Step response (10-90%)	≈ L_f L⊕ ms
Maximum temperature coefficient	< 0.01 %/K
Temperature coefficient, typical	< 0.002 %/K
Maximum transmission error	≤ 0.2 % (of final value)
Transmission error, typical	≤ 0.1 % (of final value)
electrical isolation Input/output/power supply	
Rated insulation voltage	50 V AC/DC
Test voltage	1.5 kV AC (50 Hz, 60 s)
Insulation	Basic insulation in accordance with IEC/EN 61010
Supply	
Nominal supply voltage	24 V DC
Supply voltage range	19.2 V DC 30 V DC (The DIN rail connector (ME 6,2 TBUS 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge t supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715)
Power consumption	< 900 mW (at 24 V DC and in repeater power supply operation
	< 600 mW (at 24 V DC and in isolator operation)

Input data



2864422

https://www.phoenixcontact.com/us/products/2864422

Signal: Current

Description of the input	Sensor circuit
Number of inputs	1
Current input signal	0 mA 20 mA (isolator operation)
	4 mA 20 mA (repeater power supply and isolator operation)
Max. current input signal	28 mA
Input resistance current input	approx. 50 Ω
Transmitter supply voltage	U _B - max. 4.5 V for load 0 mA 20 mA
Transmitter supply voltage range	14.7 V DC 25.5 V DC

Output data

Signal: Current

Number of outputs	1
Non-load voltage	approx. 12.5 V
Current output signal	0 mA 20 mA (isolator operation)
	4 mA 20 mA (repeater power supply and isolator operation)
Max. current output signal	28 mA
Load/output load current output	≤ 500 Ω (I = 20 mA)
Ripple	< 20 mV _{rms} (at 500 Ω)

Connection data

Connection method	Screw connection
Stripping length	12 mm
Screw thread	M3
Conductor cross section rigid	0.2 mm² 2.5 mm²
Conductor cross section flexible	0.2 mm² 2.5 mm²
Conductor cross section AWG	26 12

Dimensions

Dimensional drawing	93,1
Width	6.2 mm
Height	93.1 mm
Depth	101.2 mm

Material specifications

Color	green (RAL 6021)
Fire protection for rail vehicles (DIN EN 45545-2) R22	HL 1 - HL 2
Fire protection for rail vehicles (DIN EN 45545-2) R23	HL 1 - HL 2



2864422

https://www.phoenixcontact.com/us/products/2864422

Fire protection for rail vehicles (DIN EN 45545-2) R24	HL 1 - HL 2
Housing material	PBT
Environmental and real-life conditions	
Ambient conditions	
Degree of protection	IP20
Ambient temperature (operation)	-20 °C 60 °C
Ambient temperature (storage/transport)	-40 °C 85 °C
Altitude	≤ 2000 m
Permissible humidity (operation)	5 % 95 % (non-condensing)
Approvals	
CE	
Certificate	CE-compliant
UKCA	
Certificate	UKCA-compliant
UL, USA/Canada	14 500 D
Identification	UL 508 Recognized
	Class I, Div. 2, Groups A, B, C, D T5
Shipbuilding approval	
Certificate	DNV GL TAA000020N
DNV GL data	
Temperature	В
Humidity	В
Vibration	В
EMC	A
Enclosure	Required protection according to the Rules shall be provided upon installation on board
MC data	
Noise immunity	EN 61000-6-2
Note	When being exposed to interference, there may be minimal deviations.
Electromagnetic compatibility	Conformance with EMC directive
Noise emission	EN 61000-6-4
Electrostatic discharge	
Standards/regulations	EN 61000-4-2
Electrostatic discharge	
Comments	Safety measures must be taken to prevent electrostatic

discharge.



2864422

https://www.phoenixcontact.com/us/products/2864422

Designation Electromagnetic RF field Standards/regulations Typical deviation from the measuring range final value 10 % Fast transients (burst) Designation Fast transients (burst) Standards/regulations Typical deviation from the measuring range final value 10 % Surge current load (surge) Standards/regulations EN 61000-4-5 Surge current load (surge) Comments Conducted interference Designation Conducted interference Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Conducted interference Designation Conducted interferences Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards and regulations Electrical isolation Mounting Mounting Mounting type DIN rail mounting The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715. Mounting position any	Electromagnetic HF field	
Typical deviation from the measuring range final value Fast transients (burst) Designation Standards/regulations Typical deviation from the measuring range final value 10 % Surge current load (surge) Standards/regulations EN 61000-4-5 Surge current load (surge) Comments Criterion B Conducted interference Designation Conducted interferences Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards and regulations Electrical isolation Jaway isolation Mounting Mounting type Assembly instructions The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Designation	Electromagnetic RF field
Fast transients (burst) Designation Standards/regulations EN 61000-4-4 Typical deviation from the measuring range final value 10 % Surge current load (surge) Standards/regulations EN 61000-4-5 Surge current load (surge) Comments Conducted interference Designation Conducted interferences Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value Standards and regulations Electrical isolation 3-way isolation Mounting Mounting type DIN rail mounting Assembly instructions The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Standards/regulations	EN 61000-4-3
Designation Fast transients (burst) Standards/regulations EN 61000-4-4 Typical deviation from the measuring range final value 10 % Surge current load (surge) Standards/regulations EN 61000-4-5 Surge current load (surge) Comments Criterion B Conducted interference Designation Conducted interferences Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards and regulations Electrical isolation 3-way isolation Mounting Mounting type DIN rail mounting Assembly instructions The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Typical deviation from the measuring range final value	10 %
Standards/regulations Typical deviation from the measuring range final value 10 % Surge current load (surge) Standards/regulations EN 61000-4-5 Surge current load (surge) Comments Criterion B Conducted interference Designation Conducted interferences Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards and regulations Electrical isolation 3-way isolation Mounting Mounting type DIN rail mounting Assembly instructions The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Fast transients (burst)	
Typical deviation from the measuring range final value Surge current load (surge) Standards/regulations EN 61000-4-5 Surge current load (surge) Comments Conducted interference Designation Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value Standards and regulations Electrical isolation Standards and regulations Electrical isolation Mounting Mounting type DIN rail mounting Mounting type DIN rail connector (ME 6.2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Designation	Fast transients (burst)
Surge current load (surge) Standards/regulations EN 61000-4-5 Surge current load (surge) Comments Conducted interference Designation Conducted interferences Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards and regulations Electrical isolation 3-way isolation Mounting Mounting Mounting Assembly instructions DIN rail mounting The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Standards/regulations	EN 61000-4-4
Standards/regulations EN 61000-4-5 Surge current load (surge) Comments Conducted interference Designation Conducted interferences Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards and regulations Electrical isolation 3-way isolation Mounting Mounting Mounting type DIN rail mounting The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Typical deviation from the measuring range final value	10 %
Surge current load (surge) Comments Conducted interference Designation Conducted interferences Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards and regulations Electrical isolation 3-way isolation Mounting Mounting Mounting type Assembly instructions DIN rail mounting The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Surge current load (surge)	
Conducted interference Designation Conducted interferences Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards and regulations Electrical isolation 3-way isolation Mounting Mounting Mounting type DIN rail mounting Assembly instructions The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Standards/regulations	EN 61000-4-5
Conducted interference Designation Conducted interferences Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards and regulations Electrical isolation 3-way isolation Mounting Mounting Mounting type DIN rail mounting Assembly instructions The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Surge current load (surge)	
Designation Conducted interferences Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards and regulations Electrical isolation 3-way isolation Mounting Mounting type DIN rail mounting Assembly instructions The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.		Criterion B
Standards/regulations EN 61000-4-6 Typical deviation from the measuring range final value 10 % Standards and regulations Electrical isolation 3-way isolation Mounting Mounting type DIN rail mounting Assembly instructions The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Conducted interference	
Typical deviation from the measuring range final value 10 % Standards and regulations Electrical isolation 3-way isolation Mounting Mounting type DIN rail mounting The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Designation	Conducted interferences
Standards and regulations Electrical isolation 3-way isolation Mounting Mounting type DIN rail mounting Assembly instructions The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Standards/regulations	EN 61000-4-6
Electrical isolation 3-way isolation Mounting Mounting type DIN rail mounting The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Typical deviation from the measuring range final value	10 %
Mounting Mounting type DIN rail mounting Assembly instructions The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Standards and regulations	
Mounting type DIN rail mounting The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Electrical isolation	3-way isolation
Assembly instructions The DIN rail connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, item no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	Mounting	
no. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail in accordance with EN 60715.	-	DIN rail mounting
Mounting position any	Assembly instructions	no. 2869728) can be used to bridge the supply voltage. It can be
	Mounting position	any



2864422

https://www.phoenixcontact.com/us/products/2864422

Classifications

ECLASS

UNSPSC 21.0

27210120
27210120
27210120
EC002653

39121000



2864422

https://www.phoenixcontact.com/us/products/2864422

Environmental product compliance

REACh SVHC	Lead 7439-92-1
China RoHS	Environmentally Friendly Use Period = 50 years
	For information on hazardous substances, refer to the manufacturer's declaration available under "Downloads"

Phoenix Contact 2024 © - all rights reserved https://www.phoenixcontact.com

Phoenix Contact USA 586 Fulling Mill Road Middletown, PA 17057, United States (+717) 944-1300 info@phoenixcon.com