



### Item description

The WAGO DALI MSensor 02 is used with WAGO DALI Modules (753-647 DALI Multi-Master Module or 750-641 DALI/DSI Module). It has been designed for the following principal applications:

- Individual offices
- Open-plan offices
- Training/presentation rooms
- Corridors, passageways and garages

Subject to changes. Please also observe the further product documentation!



The Multi-Sensor features both motion and light sensor. The sensor may also be operated with an optional remote control from Tridonic. The sensor enables both motion detection and daylight-dependent lighting control, both of which can also be deactivated. Addressing is performed via rotary switch or WAGO DALI Configurator. Parameters can be adjusted individually via WAGO DALI Configurator.

Power supply is provided via the DALI line.

The number of sensors, which can be operated on a DALI line, depends on the total power consumption of the specific devices and the address range for the actuators and sensors. Due to the capacity of the DALI bus, a maximum of 16 DALI sensor couplers must be operated on the DALI Multi-Master Module (753-647).

**Installation Notes:**

- The DALI MSensor 02 is supplied directly via DALI line.
- DALI is not SELV (Safety Extra Low Voltage). The installation instructions for mains voltage therefore apply.
- The detection range of the sensor must be within the lighting area of the controlled luminaires.
- The detection ranges of the sensors must not overlap as this may impair the lighting control.
- When installed at a height other than the recommended installation height (2.5 m), the presence and light sensor might show different characteristics. If installed at a greater height, the sensitivity is reduced; the range is also reduced when installed at a lower height.
- Heaters, fans, printers and copiers located in the detection range may cause incorrect presence detection.

**Data****Technical Data**

Current consumption typ.	6 mA from DALI line
Power supply	via DALI line

**Material Data**

Weight	90 g
--------	------

**Environmental Requirements**

Surrounding air (operating) temperature	0 ... 50 °C
Surrounding air (storage) temperature	-25 ... 55 °C
Protection class	IP20

**Commercial data**

Packaging type	BOX
Country of origin	SK
GTIN	4050821708384
Customs Tariff No.	90318080000

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG  
Hansastr. 27  
32423 Minden  
Phone: +49571 887-0 | Fax: +49571 887-169  
Email: [info.de@wago.com](mailto:info.de@wago.com) | Web: [www.wago.com](http://www.wago.com)

Do you have any questions about our products?  
We are always happy to take your call at +49 (571) 887-44222.



## Counterpart

## Downloads

### Documentation

#### Data sheet

2851-8301, 2851-8302, 2851-8303, DALI Multi-Sensor, data sheet	pdf 315.8 kB	Download
--	-----------------	----------

#### Additional Information

Disposal; Electrical and electronic equipment, Packaging	V 1.0.0	pdf 265.8 kB	Download
--	---------	-----------------	----------

## Application Notes

### Application Note CoDeSys 2.3

Application note: DALI 753-647 Configuration Interface	V1.0.2	zip	Download
This application note describes the WAGO DALI Configurator, the integration of the DALI visualization for configuring various sensor types and the implementation in a program.	Apr 29, 2019	3.1 MB	

## CAD/CAE-Data

### CAE data

WSCAD Universe 2851-8303	URL	Download
--------------------------	-----	----------

## Installation Notes

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG  
Hansastr. 27  
32423 Minden  
Phone: +49571 887-0 | Fax: +49571 887-169  
Email: [info.de@wago.com](mailto:info.de@wago.com) | Web: [www.wago.com](http://www.wago.com)

Do you have any questions about our products?  
We are always happy to take your call at +49 (571) 887-44222.