



**Fuse-base, LV, 16 A, AC 400 V, D01, 3P, IEC, suitable wire 1.5 - 4 mm<sup>2</sup>, click-on mount**

**Article no. TFRN01-B**  
**Catalog No. TFRN01-B**

Similar to illustration

## Delivery program

Product range			Fuse accessory
Basic function			Fuse-base
Field of application			low voltage
Rated current	I	A	16
Rated voltage			AC 400 V
Construction size			D01
Description			suitable for 1.5 - 4 mm <sup>2</sup> connecting leads click-on mounting
Number of poles			3P
usable for size/applications			for size D01 fuse-link
Standard/Approval			IEC

## Technical data ETIM 6.0

Circuit breakers and fuses (EG000020) / D0-system fuse base (EC001644)			
Electric engineering, automation, process control engineering / Electrical installation, device / Safety fuse systems / Neozed fuse base (ecl@ss8.1-27-14-21-20 [ACN355008])			
Number of poles			3
Construction size			D01
Material			Porcelain
Version with cover			No
Mounting method			Snap mounting
Nominal rated voltage		V	400
Nominal rated current		A	16