

Star-delta contactor combination, 110kW/400V/AC3

Powering Business Worldwide*

 Part no.
 SDAINLM200(110V50HZ,120V60HZ)

 Article no.
 101007

 Catalog No.
 XTSD200G11A

Delivery program

Product range Application Accessories Utilization category Description Rated operational current AC-3 380 V 400 V Max. rating for three-phase motors, 50 - 60 Hz Contactor combinations Star-delta motor starting for contactor combinations Star-delta combinations SDAINL NAC-3: Normal AC induction motors: starting, switch off during running Operating frequency: maximum 30 starts per hour	
Accessories Utilization category Description Rated operational current AC-3 380 V 400 V Max. rating for three-phase motors, 50 - 60 Hz Star-delta combinations SDAINL NAC-3: Normal AC induction motors: starting, switch off during running Operating frequency: maximum 30 starts per hour 1	
Utilization category Description Rated operational current AC-3 380 V 400 V Max. rating for three-phase motors, 50 - 60 Hz NAC-3: Normal AC induction motors: starting, switch off during running Operating frequency: maximum 30 starts per hour A 200 Max. rating for three-phase motors, 50 - 60 Hz	
Description Rated operational current AC-3 380 V 400 V Max. rating for three-phase motors, 50 - 60 Hz Operating frequency: maximum 30 starts per hour Le A 200	
Rated operational current AC-3 380 V 400 V I _e A 200 Max. rating for three-phase motors, 50 - 60 Hz	
AC-3 380 V 400 V I _e A 200 Max. rating for three-phase motors, 50 - 60 Hz	
380 V 400 V I _e A 200 Max. rating for three-phase motors, 50 - 60 Hz	
Max. rating for three-phase motors, 50 - 60 Hz	
100	
AC-3	
220 V 230 V P kW 55	
380 V 400 V P kW 110	
500 V P kW 132	
660 V 690 V P kW 160	
Max. changeover time s 20	
Actuating voltage 110 V 50 Hz, 120 V 60 Hz	
Voltage AC/DC AC operation	
Individual components of the combination	
Mains contactor Q11 Part no. DILM115 + DILM150-XHI11	
Delta contactor Q15 Part no. DILM115 + DILM150-XHI31	
Star contactor Q13 Part no. DILM80 + DILM150-XHI11	
Timing relay K1 Part no. ETR4-51	


Design verification as per IEC/EN 61439

Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	200
Heat dissipation per pole, current-dependent	P _{vid}	W	15.7
Equipment heat dissipation, current-dependent	P _{vid}	W	47.2
Static heat dissipation, non-current-dependent	P _{vs}	W	6.6
Heat dissipation capacity	P _{diss}	W	0
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	60
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects $\frac{1}{2} = \frac{1}{2} \left(\frac{1}{2} + \frac{1}{2} \right) \left(\frac{1}{2} + \frac{1}{2} + \frac{1}{2} \right) \left(\frac{1}{2} + \frac{1}$			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.


10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Combination of contactors (EC000010)					
Electric engineering, automation, process control engineering / Low-voltage switch technology / Contactor (LV) / Combination of contactor (ecl@ss8.1-27-37-10-09 [AGZ572011])					
Function		Star-delta contactor			
Rated control supply voltage Us at AC 50HZ	V	110 - 110			
Rated control supply voltage Us at AC 60HZ	V	120 - 120			
Rated control supply voltage Us at DC	V	0 - 0			
Voltage type for actuating		AC			
Rated operation current le at AC-3, 400 V	Α	200			
Rated operation power at AC-3, 400 V	kW	110			
Type of electrical connection of main circuit		Screw connection			
Degree of protection (IP)		IP00			



Dimensions



Additional product information (links)

IL03407030Z (AWA2100-2139) Wiring for contactor combinations

IL03407030Z (AWA2100-2139) Wiring for contactor combinations

 $ftp://ftp.moeller.net/DOCUMENTATION/AWA_INSTRUCTIONS/IL03407030Z2011_07.pdf$