

**Data sheet | Item number: 750-923/000-001**  
Configuration cable; USB connector; Length: 5 m

[www.wago.com/750-923/000-001](http://www.wago.com/750-923/000-001)



### Item description

The WAGO USB Communication Cable connects a PC (notebook) to both the service interface of the 857 Series Signal Conditioners and the configuration interface of WAGO's I/O fieldbus couplers/controllers.

#### Notice!

Using the WAGO 759-923 USB Communication Cable  
in combination with select programmable fieldbus controllers  
requires the specific firmware versions listed below:

750-841: Firmware Version 12 (or higher)

750-872/0020-0000: Firmware Version 2 (or higher)

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG  
Hansastr. 27  
32423 Minden  
Phone: +49571 887-0 | Fax: +49571 887-169  
Email: [info.de@wago.com](mailto:info.de@wago.com) | Web: [www.wago.com](http://www.wago.com)

Do you have any questions about our products?  
We are always happy to take your call at +49 (571) 887-44222.



## Data

### Technical Data

Connection type	4-pole male connector - USB A-type plug
No. of poles	4
Cable length	5 m
Supported operating systems	Windows XP (SP3 or higher) Windows 7 Windows 10

### Geometrical Data

Width	15 mm / 0.591 inch
Height	50 mm / 1.97 inch
Depth	19 mm / 0.748 inch

### Mechanical data

Weight	114.3 g
--------	---------

### Environmental Requirements

Surrounding air (operating) temperature	-25 ... 70 °C
Protection class	IP20
EMC immunity to interference	per EN 61000-4-3; EN 61000-4-6
EMC emission of interference	per EN 55022

### Commercial data

Product Group	15 (Remote I/O)
Packaging type	bag
Country of origin	DE
GTIN	4045454765200
Customs Tariff No.	85444290900

### Counterpart

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG  
Hansastr. 27  
32423 Minden  
Phone: +49571 887-0 | Fax: +49571 887-169  
Email: [info.de@wago.com](mailto:info.de@wago.com) | Web: [www.wago.com](http://www.wago.com)

Do you have any questions about our products?  
We are always happy to take your call at +49 (571) 887-44222.



## Downloads

### Documentation

#### Tutorial

Set IP address with Ethernet Settings	3.0	mp4	Download
In this video we are demonstrating how you can set a IP address with Ethernet Settings. Content: 00:27 – Chapter #1 Download and install software; 00:56 – Chapter #2 Open Ethernet Settings; 01:10 – Chapter #3 Establish serial Connection; 01:34 – Chapter #4 Set IP address; 02:10 – Chapter #5 Check IP address	Dec 18, 2017	88.3 MB	

#### System Description

750/753 Series I/O-System – General Product Information		pdf 1.7 MB	Download
---	--	---------------	----------

## CAD/CAE-Data

### CAE data

EPLAN Data Portal 750-923/000-001		URL	Download
WSCAD Universe 750-923/000-001		URL	Download

## Device Files

### Device Driver

WAGO USB Service Kabel Treiber / Serie 750 und 857	6.5.3.0 Sep 10, 2014	zip 4.8 MB	Download
--	-------------------------	---------------	----------

## Installation Notes

Subject to changes. Please also observe the further product documentation!