

**SAI-T-5S-PARA****Weidmüller Interface GmbH & Co. KG**

Klingenbergstraße 26

D-32758 Detmold

Germany

Fon: +49 5231 14-0

Fax: +49 5231 14-292083

www.weidmueller.com



Individual cable lengths are often required nowadays. In order to meet these demands, Weidmüller offers a wide range of plug-in connectors for custom assembly. Y-distributors are used to bundle and distribute multiple signals to save space.

**General ordering data**

Type	SAI-T-5S-PARA
Order No.	<a href="#">1009370000</a>
Version	Y connector, M12
GTIN (EAN)	4032248713622
Qty.	1 pc(s).

Creation date May 1, 2020 4:30:53 AM CEST

Catalogue status 17.04.2020 / We reserve the right to make technical changes.

## SAI-T-5S-PARA

**Weidmüller Interface GmbH & Co. KG**  
 Klingenbergstraße 26  
 D-32758 Detmold  
 Germany  
 Fon: +49 5231 14-0  
 Fax: +49 5231 14-292083  
 www.weidmueller.com

## Technical data

## Dimensions and weights

Net weight	30 g
------------	------

## Environmental Product Compliance

REACH SVHC	Lead 7439-92-1
------------	----------------

## Connection data

Group outlet - plug-in connector	M12 socket	Single outlet 1 - plug-in connector	M12 socket
Single outlet 2 - plug-in connector	M12 pin	Tightening torque	M12: 0.8 - 1.2 Nm

## General data

Cable glands	M 12	Coding	A
Conductor O.D.	-	Connection thread	M12
Contact material	CuSn	Contact surface	Gold-plated
Number of poles	5	Pollution severity	3
Protection degree	IP67	Rated current	4 A
Rated voltage	60 V	Temperature range of housing	-25...+85 °C

## Classifications

ETIM 6.0	EC002925	ETIM 7.0	EC002925
eClass 9.0	27-44-01-06	eClass 9.1	27-44-01-06
eClass 10.0	27-44-01-06		

## Approvals

Approvals



ROHS	Conform
------	---------

## Downloads

Brochure/Catalogue	<a href="#">CAT 8 SAI 15/16 EN</a> <a href="#">FL FIELDWIRING EN</a>
Engineering Data	<a href="#">EPLAN</a>

**SAI-T-5S-PARA**

**Weidmüller Interface GmbH & Co. KG**  
Klingenbergstraße 26  
D-32758 Detmold  
Germany  
Fon: +49 5231 14-0  
Fax: +49 5231 14-292083  
[www.weidmueller.com](http://www.weidmueller.com)

**Drawings**

**Wiring diagram**

